

From Swisscom (Schweiz) AG
Issue Date 18.05.2016
Subject WSG ListOfValues

WSG Lists Of Values

Status productive version

Version 3

Replaces Version

Valid from 30.05.2016 (WSG_9.16 / May16)

Valid until recall or replacement by a new version

Contents

Revisions.....	2
Release	2
Contents	3
1 Introduction.....	4
1.1 General Information.....	4
1.2 ListOfValue Ranges.....	4
2 List of values in WSG.....	5

1 Introduction

1.1 General Information

This document contains defined list of values for the WSG application which are used by the B2B Interfaces.
All list of values in the WSG are usually written in English. Please be aware that any element in any listofvalue text can be changed at any time without further notice.

1.2 ListOfValue Ranges

In general the following rules are applied in general:

LOV_IDs under 1000 are values related to copper- functionality (APV).

LOV_IDs under 3000 are values related to broadband functionality and general LOV's.

LOV_IDs under 5000 are values related to assurance (TT).

LOV_IDs under 6000 are values related to COPA functionality.

LOV_IDs under 8000 are values related to IPPool functionality

2 List of values in WSG

Lov Id	Lov Name	Comment	Lov Value	Description	Alternative Description	Comment
107	LOV_SG_MM	sgMm	1	1 - normal	1 - normal	
107	LOV_SG_MM	sgMm	2	2 - by customer	2 - by customer	
107	LOV_SG_MM	sgMm	3	3 - by service partner	3 - by service partner	
109	LOV_DN_TYPE	dnType	1	Economy Line		
109	LOV_DN_TYPE	dnType	6	Multi Line		
109	LOV_DN_TYPE	dnType	7	Multi Line (MSN)		
109	LOV_DN_TYPE	dnType	11	Business Line		
109	LOV_DN_TYPE	dnType	13	Netservices number		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	1	Basel		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	2	Bellinzona		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	3	Bern		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	4	Biel		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	5	Chur		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	6	Freiburg		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	7	Genf		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	8	Lausanne		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	9	Luzern		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	10	Neuenburg		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	11	Olten		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	12	Rapperswil		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	13	St. Gallen		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	14	Sitten		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	15	Thun		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	16	Winterthur		
113	LOV_APV_OFFICE_CODE	Geschäftsstelle	17	Zürich		
115	LOV_UP_KONTAKT_ART	contactType	1	UPK	Überführungskontakt	
115	LOV_UP_KONTAKT_ART	contactType	2	UPKL	Überführungskontakt links	
115	LOV_UP_KONTAKT_ART	contactType	3	UPKR	Überführungskontakt rechts	

115	LOV_UP_KONTAKT_ART	contactType	4	EK	Endstellenkontakt	
115	LOV_UP_KONTAKT_ART	contactType	5	S	Stammkontakt	
115	LOV_UP_KONTAKT_ART	contactType	6	V	Verteilerkontakt	
115	LOV_UP_KONTAKT_ART	contactType	7	A	Ausgleichskontakt	
115	LOV_UP_KONTAKT_ART	contactType	8	R	Reservekontakt	
115	LOV_UP_KONTAKT_ART	contactType	9	TLK1	Trennlistenkontakt 1	
115	LOV_UP_KONTAKT_ART	contactType	10	LDK	Leitungsdurchschalterkontakt	
115	LOV_UP_KONTAKT_ART	contactType	11	BLK	Betriebsleitungskontakt	
115	LOV_UP_KONTAKT_ART	contactType	12	LK	Linienkontakt	
115	LOV_UP_KONTAKT_ART	contactType	13	RVK	Rückverbinderkontakt	
115	LOV_UP_KONTAKT_ART	contactType	14	KK	Kabelkontakt	
115	LOV_UP_KONTAKT_ART	contactType	15	TLK2	Trennlistenkontakt 2	
115	LOV_UP_KONTAKT_ART	contactType	16	TLK3	Trennlistenkontakt 3	
115	LOV_UP_KONTAKT_ART	contactType	17	TLK4	Trennlistenkontakt 4	
115	LOV_UP_KONTAKT_ART	contactType	18	TLK5	Trennlistenkontakt 5	
115	LOV_UP_KONTAKT_ART	contactType	19	TLK6	Trennlistenkontakt 6	
115	LOV_UP_KONTAKT_ART	contactType	20	TLK7	Trennlistenkontakt 7	
115	LOV_UP_KONTAKT_ART	contactType	21	TLK8	Trennlistenkontakt 8	
115	LOV_UP_KONTAKT_ART	contactType	22	TLK9	Trennlistenkontakt 9	
115	LOV_UP_KONTAKT_ART	contactType	23	RKK	Regionalkabelkontakt	
115	LOV_UP_KONTAKT_ART	contactType	24	OC	Optischer Kontakt	
115	LOV_UP_KONTAKT_ART	contactType	25	ALK	Abgesetzter Linienkontakt (AVE)	
115	LOV_UP_KONTAKT_ART	contactType	26	LAK	Leitungs-ausrüstungskontakt	
115	LOV_UP_KONTAKT_ART	contactType	27	CXC	Koaxialkontakt	
115	LOV_UP_KONTAKT_ART	contactType	28	OCB	Optischer Kontakt Bundeshaus (nur Bern)	
115	LOV_UP_KONTAKT_ART	contactType	30	HSK	Hausschienenkontakt	
115	LOV_UP_KONTAKT_ART	contactType	31	PS	Port Switch Kontakt	
115	LOV_UP_KONTAKT_ART	contactType	32	PL	Port Line Kontakt	
115	LOV_UP_KONTAKT_ART	contactType	33	AS1	xDSL Switch Kontakt 1	
115	LOV_UP_KONTAKT_ART	contactType	34	AS2	xDSL Switch Kontakt 2	
115	LOV_UP_KONTAKT_ART	contactType	35	AS3	xDSL Switch Kontakt 3	
115	LOV_UP_KONTAKT_ART	contactType	36	AS4	xDSL Switch Kontakt 4	
115	LOV_UP_KONTAKT_ART	contactType	37	AS5	xDSL Switch Kontakt 5	
115	LOV_UP_KONTAKT_ART	contactType	38	AS6	xDSL Switch Kontakt 6	
115	LOV_UP_KONTAKT_ART	contactType	39	AS7	xDSL Switch Kontakt 7	
115	LOV_UP_KONTAKT_ART	contactType	40	AS8	xDSL Switch Kontakt 8	
115	LOV_UP_KONTAKT_ART	contactType	41	AS9	xDSL Switch Kontakt 9	
115	LOV_UP_KONTAKT_ART	contactType	42	AL1	xDSL Line Kontakt 1	

115	LOV_UP_KONTAKT_ART	contactType	43	AL2	xDSL Line Kontakt 2	
115	LOV_UP_KONTAKT_ART	contactType	44	AL3	xDSL Line Kontakt 3	
115	LOV_UP_KONTAKT_ART	contactType	45	AL4	xDSL Line Kontakt 4	
115	LOV_UP_KONTAKT_ART	contactType	46	AL5	xDSL Line Kontakt 5	
115	LOV_UP_KONTAKT_ART	contactType	47	AL6	xDSL Line Kontakt 6	
115	LOV_UP_KONTAKT_ART	contactType	48	AL7	xDSL Line Kontakt 7	
115	LOV_UP_KONTAKT_ART	contactType	49	AL8	xDSL Line Kontakt 8	
115	LOV_UP_KONTAKT_ART	contactType	50	AL9	xDSL Line Kontakt 9	
115	LOV_UP_KONTAKT_ART	contactType	51	XDF1	ULL Line Kontakt 1	
115	LOV_UP_KONTAKT_ART	contactType	52	XDF2	ULL Line Kontakt 2	
115	LOV_UP_KONTAKT_ART	contactType	53	XDF3	ULL Line Kontakt 3	
115	LOV_UP_KONTAKT_ART	contactType	54	XDF4	ULL Line Kontakt 4	
115	LOV_UP_KONTAKT_ART	contactType	55	XDF5	ULL Line Kontakt 5	
115	LOV_UP_KONTAKT_ART	contactType	56	XDF6	ULL Line Kontakt 6	
115	LOV_UP_KONTAKT_ART	contactType	57	XDF7	ULL Line Kontakt 7	
115	LOV_UP_KONTAKT_ART	contactType	58	XDF8	ULL Line Kontakt 8	
115	LOV_UP_KONTAKT_ART	contactType	59	XDF9	ULL Line Kontakt 9	
126	LOV_S_D_UEB	S_D_UEB	1	eroeffnet		
126	LOV_S_D_UEB	S_D_UEB	2	erledigt		
126	LOV_S_D_UEB	S_D_UEB	3	annulliert		
205	LOV_YES_NO	bbAccess	1	Yes		
205	LOV_YES_NO	bbAccess	2	No		
245	LOV_SYNCH_TYPE	SYNCH_TYPE	1	No Synch.		
245	LOV_SYNCH_TYPE	SYNCH_TYPE	2	Synch BBCS-TDM (SG-MM1)		
245	LOV_SYNCH_TYPE	SYNCH_TYPE	3	OSI-SAT		
245	LOV_SYNCH_TYPE	SYNCH_TYPE	4	Access Synch / Change Case		
245	LOV_SYNCH_TYPE	SYNCH_TYPE	5	Synch TDM to Standalone (SAT - OK)		
245	LOV_SYNCH_TYPE	SYNCH_TYPE	6	TAL	TAL	
245	LOV_SYNCH_TYPE	SYNCH_TYPE	7	2x P3301		
268	LOV_BB_NUMBER_OF_WIRES	nrOfWires	1	2 wires		
268	LOV_BB_NUMBER_OF_WIRES	nrOfWires	2	4 wires		
268	LOV_BB_NUMBER_OF_WIRES	nrOfWires	3	6 wires		
268	LOV_BB_NUMBER_OF_WIRES	nrOfWires	4	8 wires		
272	LOV_BB_ACTION	ULL_TECH_ACTION	1	Hinzufügen		
272	LOV_BB_ACTION	ULL_TECH_ACTION	2	Mutieren		
272	LOV_BB_ACTION	ULL_TECH_ACTION	3	Unverändert		

276	LOV_BB_TYPE	bbType	1	ADSL	ADSL	
276	LOV_BB_TYPE	bbType	2	VDSL	VDSL2	
276	LOV_BB_TYPE	bbType	3	SDSL	SDSL	
276	LOV_BB_TYPE	bbType	8	Alternative	ALTERNATIV	
276	LOV_BB_TYPE	bbType	10	FTTH	FTTH	WSG 9.4 FTTH_Pilot removed
276	LOV_BB_TYPE	bbType	11	BX	BX	Fiber
276	LOV_BB_TYPE	bbType	21	ALO	ALO	Nov10-Release
281	LOV_BB_PORT_TYPE	bbPortType	1	analog		
281	LOV_BB_PORT_TYPE	bbPortType	2	ISDN		
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	1	Basic		
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	2	Premium		
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	3	Express - billed to ISP		Express_SF-SLA for ISPs (heute fuer morgen)
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	4	Express Swisscom Fault		Express_SF-SLA for SCS (heute fuer morgen)
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	6	Express - Assurance		
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	7	Express - IFUF		
282	LOV_BB_SF_EXCEPTION_PRIO	sfSlald	8	OSISynch		
283	LOV_BB_LEVEL_OF_SUP_SERV	saSlald	1	Standard	STANDARD	
283	LOV_BB_LEVEL_OF_SUP_SERV	saSlald	4	Intermediate	INTERMEDIATE	Released for V8.2
283	LOV_BB_LEVEL_OF_SUP_SERV	saSlald	2	Plus	PLUS	
283	LOV_BB_LEVEL_OF_SUP_SERV	saSlald	5	Event based	EVENT-BASED	
286	LOV_APV_WB_286	BB ASAM Type	1	ASAM		
286	LOV_APV_WB_286	BB ASAM Type	2	ISAM@EAP		
286	LOV_APV_WB_286	BB ASAM Type	3	CAN@EAP		
286	LOV_APV_WB_286	BB ASAM Type	4	ISAM@WARP		
286	LOV_APV_WB_286	BB ASAM Type	5	CAN@WARP		
286	LOV_APV_WB_286	BB ASAM Type	6	BCAN@RAMPplus		
286	LOV_APV_WB_286	BB ASAM Type	7	BCAN@WARP		
291	LOV_APV_WB_291	CFU_A/D_mode	1	fest mit 1 Umleitziel		
291	LOV_APV_WB_291	CFU_A/D_mode	2	fest, BA-Dienste mit verschiedenen Umleitzielen		
291	LOV_APV_WB_291	CFU_A/D_mode	3	steuerbar		
298	LOV_APV_WB_298	Baugruppenart	1	HV	Hauptverteiler	
298	LOV_APV_WB_298	Baugruppenart	2	VT	Verteiler	
298	LOV_APV_WB_298	Baugruppenart	3	UP	Überführungspunkt	
298	LOV_APV_WB_298	Baugruppenart	4	EST	Endstelle	

298	LOV_APV_WB_298	Baugruppenart	5	AVE	Abgesetzte Vermittlungseinheit	
320	CONTR_ELEMENT	contractElement	120	BBCS_Standalone		
320	CONTR_ELEMENT	contractElement	110	BBCS_on_TDM		
320	CONTR_ELEMENT	contractElement	220	DBC - DSL_Base_Connectivity		
320	CONTR_ELEMENT	contractElement	840	LCS - LEC Basic Connectivity 2Net		
320	CONTR_ELEMENT	contractElement	830	LCS - LEC Basic Connectivity		
320	CONTR_ELEMENT	contractElement	420	BBCS_F (Fiber)		
320	CONTR_ELEMENT	contractElement	530	Incoming L1C Order (Kopa->SCS)		
320	CONTR_ELEMENT	contractElement	540	Outgoing Fiber Inhouse Order (SCS->Kopa)		
320	CONTR_ELEMENT	contractElement	430	ALO Layer 1		
320	CONTR_ELEMENT	contractElement	431	ALO Service		
320	CONTR_ELEMENT	contractElement	100	Best Effort		
320	CONTR_ELEMENT	contractElement	440	L1 Provider		
320	CONTR_ELEMENT	contractElement	441	L1 Solution		
320	CONTR_ELEMENT	contractElement	9	Streaming		
320	CONTR_ELEMENT	contractElement	12	Real Time		
320	CONTR_ELEMENT	contractElement	450	Fiber Rental		
320	CONTR_ELEMENT	contractElement	101	Best Effort on Fiber		
320	CONTR_ELEMENT	contractElement	490	FBC		
320	CONTR_ELEMENT	contractElement	19	Full Access (TAL)		
320	CONTR_ELEMENT	contractElement	22	Full Access Subloop (T-TAL)		
320	CONTR_ELEMENT	contractElement	910	BBCS_on_Fiber (FTTH-Pilot)		
320	CONTR_ELEMENT	contractElement	820	CIS & LAN-I Basis (no Prov.)		
320	CONTR_ELEMENT	contractElement	7	BBCS_ISP Private		
320	CONTR_ELEMENT	contractElement	8	BBCS_ISP Business		
320	CONTR_ELEMENT	contractElement	10	BBCS_Light_ISP		
320	CONTR_ELEMENT	contractElement	13	BBCS_DHCP Private		
320	CONTR_ELEMENT	contractElement	14	BBCS_DHCP Business		
320	CONTR_ELEMENT	contractElement	18	BBCS_DHCP Light		
320	CONTR_ELEMENT	contractElement	16	2nd line VoIP		
320	CONTR_ELEMENT	contractElement	15	IP-Centrex		
376	LOV_ULL_TYPE	ULL_TYPE	1	Full Access		
376	LOV_ULL_TYPE	ULL_TYPE	2	Full Access Subloop	Full Access Subloop	
382	LOV_ULL_TECH	ULL_TECH	1	classical ADSL	ADSL	
382	LOV_ULL_TECH	ULL_TECH	2	VDSL	VDSL2	
382	LOV_ULL_TECH	ULL_TECH	3	SDSL	SDSL	
382	LOV_ULL_TECH	ULL_TECH	4	HDSL	HDSL	

382	LOV_ULL_TECH	ULL_TECH	5	HDSL2B1Q	HDSL2B1Q	
382	LOV_ULL_TECH	ULL_TECH	6	HDSL2CAP	HDSL2CAP	
382	LOV_ULL_TECH	ULL_TECH	7	POTS	POTS	
382	LOV_ULL_TECH	ULL_TECH	8	ISDN	ISDN	
382	LOV_ULL_TECH	ULL_TECH	9	ADSL2+	ADSL2+	
400	LOV_APV_WB_400	SRC_SYSTEM	1	TERCO		
400	LOV_APV_WB_400	SRC_SYSTEM	2	ISLK		
400	LOV_APV_WB_400	SRC_SYSTEM	3	UNI-CURU		
400	LOV_APV_WB_400	SRC_SYSTEM	4	TEDIS/TAV		
400	LOV_APV_WB_400	SRC_SYSTEM	5	WSG		
400	LOV_APV_WB_400	SRC_SYSTEM	6	EBAK		
400	LOV_APV_WB_400	SRC_SYSTEM	7	CSS/IN		
400	LOV_APV_WB_400	SRC_SYSTEM	8	Bridge		
401	LOV_APV_WB_401	BB_ADSL_EMU	1	No		
401	LOV_APV_WB_401	BB_ADSL_EMU	2	Yes		
1001	LOV_ORDER_TYPE	orderType	1	BBCS_CREATE	SRV_CREATE	
1001	LOV_ORDER_TYPE	orderType	2	BBCS_MODIFY	SRV_MODIFY	
1001	LOV_ORDER_TYPE	orderType	3	BBCS_DISCONNECT	SRV_DISCON	
1001	LOV_ORDER_TYPE	orderType	4	BBCS_GETSTATUS	GET_SRV_STATUS	
1001	LOV_ORDER_TYPE	orderType	8	ISP_CHANGE	SRV_CHANGE_ISP	
1001	LOV_ORDER_TYPE	orderType	9	GET_BUSINESS_LINES	GET_BUSINESS_LINES	
1001	LOV_ORDER_TYPE	orderType	10	ISP_CHANGE DONOR	ISP_CHANGE_DONOR	
1001	LOV_ORDER_TYPE	orderType	11	GET_DSLAM_PORT_STATUS	GET_DSLAM_PORT_STATUS	
1001	LOV_ORDER_TYPE	orderType	12	GET_UNICURU_STATUS	GET_UNICURU_STATUS	
1001	LOV_ORDER_TYPE	orderType	13	SRV_ADD	SRV_ADD	
1001	LOV_ORDER_TYPE	orderType	14	SRV_REDUCE	SRV_REDUCE	
1001	LOV_ORDER_TYPE	orderType	16	GET_XDSL_PORT	GET_XDSL_PORT	
1001	LOV_ORDER_TYPE	orderType	17	SRV_MAINT	SRV_MAINT	
1001	LOV_ORDER_TYPE	orderType	18	SRV_CHANGE	SRV_CHANGE	
1001	LOV_ORDER_TYPE	orderType	20	RESCHEDULE_APV_ORDER	AOR_RESCHEDULE	
1002	LOV_ORDER_STATE	orderState	1	ENTERED	The new order was just entered in the WSG DB	
1002	LOV_ORDER_STATE	orderState	2	HOLDING	The order is waiting until the activation date is reached	
1002	LOV_ORDER_STATE	orderState	3	PRE_REJECTED	The Service Qualification check failed	
1002	LOV_ORDER_STATE	orderState	4	CHECKED	All checks ok, order is ready for processing in APV	
1002	LOV_ORDER_STATE	orderState	5	PROCESSING	The order was sent to OMS for processing	
1002	LOV_ORDER_STATE	orderState	6	ACCEPTED	The order was accepted by APV and is being processed	

1002	LOV_ORDER_STATE	orderState	7	EXECUTED	The order was executed successfully	
1002	LOV_ORDER_STATE	orderState	8	REJECTED	The order was rejected by OMS or APV	
1002	LOV_ORDER_STATE	orderState	9	DELAYED	The order is delayed in APV	
1002	LOV_ORDER_STATE	orderState	10	CANCEL PENDING	WSG tries to cancel the pending APV order	
1002	LOV_ORDER_STATE	orderState	11	CANCELLED	The order was cancelled	
1002	LOV_ORDER_STATE	orderState	12	PLANNED	For this office are temporarily no more ADSL ports available.	
1002	LOV_ORDER_STATE	orderState	13	COMPLETED	Filed force has activated the line.	
1002	LOV_ORDER_STATE	orderState	14	EXCEPTION	"Geschäftsabschluss" Terco with termination code unequal 3 was terminating the order.	
1002	LOV_ORDER_STATE	orderState	15	PARKED	This order is parked because of flow-control.	
1002	LOV_ORDER_STATE	orderState	16	ONSITE_PENDING	The order waits for the end of the onsite installation.	
1003	LOV_CREATION_TYPE	creationType	1	New		
1003	LOV_CREATION_TYPE	creationType	3	Promotion		
1003	LOV_CREATION_TYPE	creationType	4	Synchronisation with voice		
1003	LOV_CREATION_TYPE	creationType	5	MIG_01		
1003	LOV_CREATION_TYPE	creationType	6	MIG_03		
1003	LOV_CREATION_TYPE	creationType	7	MIG_13		
1003	LOV_CREATION_TYPE	creationType	8	MIG_08		
1003	LOV_CREATION_TYPE	creationType	9	MIG_14		
1003	LOV_CREATION_TYPE	creationType	10	MIG_62		
1004	LOV_BB_OK_STATUS	bbOkStatus	0	Field Force ready missing / Config ready missing		
1004	LOV_BB_OK_STATUS	bbOkStatus	1	Field Force ready ok / Config ready missing		
1004	LOV_BB_OK_STATUS	bbOkStatus	2	Field Force ready missing / Config ready ok		
1004	LOV_BB_OK_STATUS	bbOkStatus	3	Field Force ready ok / Config ready ok		
1005	LOV_SESSION_TYPE	sessionType	1	PPP		
1005	LOV_SESSION_TYPE	sessionType	2	DHCP		
1006	LOV_TERMINATION	termination	1	@ISP		
1006	LOV_TERMINATION	termination	2	@FWS		
1006	LOV_TERMINATION	termination	3	@DHCP		
1007	LOV_POOL_TYPE	poolType	1	pool1		
1007	LOV_POOL_TYPE	poolType	2	pool2		
1008	LOV_INTERLEAVE_MODE	interleaveMode	1	Fastpath		
1008	LOV_INTERLEAVE_MODE	interleaveMode	2	Interleave Low		

1008	LOV_INTERLEAVE_MODE	interleaveMode	3	Interleave Medium		
1008	LOV_INTERLEAVE_MODE	interleaveMode	4	Interleave High-1		VDSL Stabilisierung BBMar10
1008	LOV_INTERLEAVE_MODE	interleaveMode	5	Interleave High-2		VDSL Stabilisierung BBMar10
1008	LOV_INTERLEAVE_MODE	interleaveMode	6	Interleave High-3		VDSL Stabilisierung BBMar10
1008	LOV_INTERLEAVE_MODE	interleaveMode	11	Interleave G.INP		
1008	LOV_INTERLEAVE_MODE	interleaveMode	131	Interleave G.FAST Noise Margin 6_6		neuer Eintrag für Nov15
1008	LOV_INTERLEAVE_MODE	interleaveMode	191	Interleave G.FAST Noise Margin 9_9		neuer Eintrag für Nov15
1008	LOV_INTERLEAVE_MODE	interleaveMode	221	Interleave G.FAST Noise Margin 12_12		neuer Eintrag für Nov15
1008	LOV_INTERLEAVE_MODE	interleaveMode	251	Interleave G.FAST Noise Margin 15_15		neuer Eintrag für Nov15
1008	LOV_INTERLEAVE_MODE	interleaveMode	281	Interleave G.FAST Noise Margin 18_18		neuer Eintrag für Nov15
1009	LOV_BB_QUALITY	bbQuality	1	fix		
1009	LOV_BB_QUALITY	bbQuality	2	flex		
1009	LOV_BB_QUALITY	bbQuality	3	best effort		
1010	SPEED_PROFILE	speedProfileNr	997	11 down / 11 up		Access Reservation Profile, ADSL & VDSL
1010	SPEED_PROFILE	speedProfileNr	202	max 3500 down / 300 up		
1010	SPEED_PROFILE	speedProfileNr	204	max 15000 down / 1000 up		
1010	SPEED_PROFILE	speedProfileNr	201	max 2000 down / 100 up		
1010	SPEED_PROFILE	speedProfileNr	212	max 4000 down / 600 up		
1010	SPEED_PROFILE	speedProfileNr	221	16000 down / 4000 up		
1010	SPEED_PROFILE	speedProfileNr	216	max 12000 down / 2000 up		
1010	SPEED_PROFILE	speedProfileNr	218	12000 down / 2000 up		
1010	SPEED_PROFILE	speedProfileNr	222	max 16000 down / 4000 up		
1010	SPEED_PROFILE	speedProfileNr	7	2400 down / 500 up		
1010	SPEED_PROFILE	speedProfileNr	10	600 down / 500 up		
1010	SPEED_PROFILE	speedProfileNr	214	4000 down / 600 up		
1010	SPEED_PROFILE	speedProfileNr	225	20000 down / 4000 up		
1010	SPEED_PROFILE	speedProfileNr	200	max 300 down / 100 up		inaktives SERVICE- Profil (in ISP-SLA nicht mehr enabled)
1010	SPEED_PROFILE	speedProfileNr	404	300 down / 100 up		Service-Profil FTTH-Pilot [Dez09] (inaktiv)
1010	SPEED_PROFILE	speedProfileNr	239	max500 down / 100 up		SERVICE-Profil on- TDM, ADSL & VDSL

1010	SPEED_PROFILE	speedProfileNr	275	500 down / 500 up		BBFeb14
1010	SPEED_PROFILE	speedProfileNr	205	max 1000 down / 100 up		inaktives SERVICE- Profil (in ISP-SLA nicht mehr enabled)
1010	SPEED_PROFILE	speedProfileNr	403	1000 down / 100 up		Service-Profil FTTH-Pilot [Sep09] (inaktiv)
1010	SPEED_PROFILE	speedProfileNr	410	1000 down / 100 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	240	max2000 down / 200 up		SERVICE-Profil on- TDM & Standalone, ADSL & VDSL
1010	SPEED_PROFILE	speedProfileNr	241	max2000 down / 200 up (PAYG)		SERVICE-Profil on- TDM, ADSL & VDSL, aktiv ab Dez12
1010	SPEED_PROFILE	speedProfileNr	449	2000 down / 200 up		SERVICE-Profil FIBER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	248	max2000 down / 400 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	450	2000 down / 400 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	249	max2000 down / 2000 up		SERVICE-Profil COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	451	2000 down / 2000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	8	300 down / 300 up		inaktives SERVICE- Profil (in ISP-SLA nicht mehr enabled)
1010	SPEED_PROFILE	speedProfileNr	211	max 600 down / 600 up		inaktives SERVICE- Profil (in ISP-SLA nicht mehr enabled)
1010	SPEED_PROFILE	speedProfileNr	217	600 down / 600 up		inaktives SERVICE- Profil (in ISP-SLA nicht mehr enabled)
1010	SPEED_PROFILE	speedProfileNr	250	max2500 down / 250 up		SERVICE-Profil COPPER (10:1)
1010	SPEED_PROFILE	speedProfileNr	452	2500 down / 250 up		SERVICE-Profil FIBER (10:1)
1010	SPEED_PROFILE	speedProfileNr	251	max2500 down / 500 up		SERVICE-Profil COPPER (5:1)
1010	SPEED_PROFILE	speedProfileNr	453	2500 down / 500 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	252	max2500 down / 2500 up		SERVICE-Profil COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	454	2500 down / 2500 up		SERVICE-Profil FIBER (1:1)

1010	SPEED_PROFILE	speedProfileNr	27	4400 down / 400 up		Streaming- SERVICE-Profil ADSL/ADSL2+
1010	SPEED_PROFILE	speedProfileNr	203	max5000 down / 500 up		SERVICE-Profil, on-TDM & Standalone & DBC
1010	SPEED_PROFILE	speedProfileNr	233	max5000 down / 500 up		SERVICE-Profil BSA only, ADSL (inaktiv)
1010	SPEED_PROFILE	speedProfileNr	411	5000 down / 500 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	253	max5000 down / 1000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	455	5000 down / 1000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	254	max5000 down / 5000 up		SERVICE-Profil COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	456	5000 down / 5000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	213	max6000 down / 600 up		SERVICE-Profil on- TDM, ADSL (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	215	6000 down / 600 up		SERVICE-Profil on- TDM, VDSL (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	219	1200 down / 1200 up		SERVICE-Profil SA, SDSL (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	220	1800 down / 1800 up		SERVICE-Profil SA, SDSL (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	228	2000 down / 2000 up		SERVICE-Profil on- TDM & SA, VDSL
1010	SPEED_PROFILE	speedProfileNr	439	2000 down / 2000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	255	max8000 down / 800 up		SERVICE-Profil COPPER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	457	8000 down / 800 up		SERVICE-Profil FIBER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	256	max8000 down / 1600 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	458	8000 down / 1600 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	257	max8000 down / 8000 up		SERVICE-Profil

						COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	459	8000 down / 8000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	229	4000 down / 4000 up		SERVICE-Profil on- TDM & SA, VDSL
1010	SPEED_PROFILE	speedProfileNr	440	4000 down / 4000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	209	max10000 down / 1000 up		SERVICE-Profil on- TDM & SA (ab Aug13 auch ADSL)
1010	SPEED_PROFILE	speedProfileNr	412	10000 down / 1000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	258	max10000 down / 2000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	413	10000 down / 2000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	259	max10000 down / 10000 up		SERVICE-Profil COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	460	10000 down / 10000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	414	15000 down / 500 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	415	15000 down / 1000 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	207	max15000 down / 1500 up		SERVICE-Profil, per Aug13 neu definiert
1010	SPEED_PROFILE	speedProfileNr	461	15000 down / 1500 up		SERVICE-Profil FIBER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	416	15000 down / 2000 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	261	max15000 down / 3000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	417	15000 down / 3000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	262	max15000 down / 15000 up		SERVICE-Profil COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	462	15000 down / 15000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	224	max 16000 down / 2000 up		inaktives SERVICE- Profil (in ISP-SLA)

						nicht mehr enabled)
1010	SPEED_PROFILE	speedProfileNr	223	16000 down / 2000 up		inaktives SERVICE-Profil (in ISP-SLA nicht mehr enabled) - seit Juni 2009 passiv
1010	SPEED_PROFILE	speedProfileNr	210	max 20000 down / 1000 up		passives SERVICE-Profil, on-TDM and Standalone and DBC [passiv ab Nov10]
1010	SPEED_PROFILE	speedProfileNr	418	20000 down / 1000 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	230	max20000 down / 2000 up		SERVICE-Profil on-TDM & SA (ab Aug13 auch ADSL)
1010	SPEED_PROFILE	speedProfileNr	419	20000 down / 2000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	231	20000 down / 3000 up		SERVICE-Profil on-TDM, VDSL (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	420	20000 down / 3000 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	263	max20000 down / 4000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	463	20000 down / 4000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	232	20000 down / 5000 up		SERVICE-Profil on-TDM, VDSL (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	234	6000 down / 6000 up		SERVICE-Profil on-TDM & SA, VDSL
1010	SPEED_PROFILE	speedProfileNr	441	6000 down / 6000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	264	max20000 down / 20000 up		SERVICE-Profil COPPER (1:1)
1010	SPEED_PROFILE	speedProfileNr	464	20000 down / 20000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	421	25000 down / 1000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	422	25000 down / 2000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	265	max25000 down / 2500 up		SERVICE-Profil COPPER (10:1) [Aug13]

1010	SPEED_PROFILE	speedProfileNr	465	25000 down / 2500 up		SERVICE-Profil FIBER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	423	25000 down / 3000 up		SERVICE-Profil FIBER (ab Aug13 passiv)
1010	SPEED_PROFILE	speedProfileNr	266	max25000 down / 5000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	424	25000 down / 5000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	425	25000 down / 6000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	235	8000 down / 8000 up		SERVICE-Profil on- TDM & SA, VDSL
1010	SPEED_PROFILE	speedProfileNr	442	8000 down / 8000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	236	10000 down / 10000 up		SERVICE-Profil on- TDM & SA, VDSL
1010	SPEED_PROFILE	speedProfileNr	443	10000 down / 10000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	444	20000 down / 20000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	284	max25000 down / 25000 up		SERVICE-Profil COPPER (1:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	466	25000 down / 25000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	426	30000 down / 1000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	427	30000 down / 2000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	237	max30000 down / 3000 up		SERVICE-Profil on- TDM & SA (ab Aug13 auch ADSL)
1010	SPEED_PROFILE	speedProfileNr	238	max30000 down / 3000 up		SERVICE-Profil BSA only, VDSL (inaktiv)
1010	SPEED_PROFILE	speedProfileNr	401	30000 down / 3000 up		Service-Profil FTTH-Pilot [Jan09] (inaktiv)
1010	SPEED_PROFILE	speedProfileNr	428	30000 down / 3000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	429	30000 down / 5000 up		SERVICE-Profil FIBER (ab Nov13)

						passiv)
1010	SPEED_PROFILE	speedProfileNr	267	max30000 down / 6000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	430	30000 down / 6000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	285	max30000 down / 30000 up		SERVICE-Profil COPPER (1:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	445	30000 down / 30000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	467	30000 down / 30000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	260	max40000 down / 4000 up		SERVICE-Profil COPPER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	488	40000 down / 4000 up		SERVICE-Profil FIBER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	272	max40000 down / 8000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	493	40000 down / 8000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	286	max40000 down / 40000 up		SERVICE-Profil COPPER (1:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	405	40000 down / 40000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	431	50000 down / 3000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	242	max50000 down / 5000 up		SERVICE-Profil on- TDM & SA (ab Aug13 auch ADSL)
1010	SPEED_PROFILE	speedProfileNr	432	50000 down / 5000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	433	50000 down / 6000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	246	max50000 down / 10000 up		SERVICE-Profil on- TDM & SA (ab Aug13 auch ADSL)
1010	SPEED_PROFILE	speedProfileNr	402	50000 down / 10000 up		Service-Profil FTTH-Pilot [Jan09] (inaktiv)
1010	SPEED_PROFILE	speedProfileNr	434	50000 down / 10000 up		SERVICE-Profil FIBER

						(asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	287	max50000 down / 50000 up		SERVICE-Profil COPPER (1:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	446	50000 down / 50000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	468	50000 down / 50000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	270	max60000 down / 6000 up		SERVICE-Profil COPPER (10:1)
1010	SPEED_PROFILE	speedProfileNr	489	60000 down / 6000 up		SERVICE-Profil FIBER (10:1)
1010	SPEED_PROFILE	speedProfileNr	273	max60000 down / 12000 up		SERVICE-Profil COPPER (5:1)
1010	SPEED_PROFILE	speedProfileNr	494	60000 down / 12000 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	406	60000 down / 60000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	268	max75000 down / 7500 up		SERVICE-Profil COPPER (10:1)
1010	SPEED_PROFILE	speedProfileNr	469	75000 down / 7500 up		SERVICE-Profil FIBER (10:1)
1010	SPEED_PROFILE	speedProfileNr	269	max75000 down / 15000 up		SERVICE-Profil COPPER (5:1)
1010	SPEED_PROFILE	speedProfileNr	470	75000 down / 15000 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	471	75000 down / 75000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	271	max80000 down / 8000 up		SERVICE-Profil COPPER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	490	80000 down / 8000 up		SERVICE-Profil FIBER (10:1) [Aug13]
1010	SPEED_PROFILE	speedProfileNr	274	max80000 down / 16000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	495	80000 down / 16000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	288	max80000 down / 80000 up		SERVICE-Profil COPPER (1:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	407	80000 down / 80000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	435	100000 down / 5000 up		SERVICE-Profil FIBER (ab Nov13 passiv)
1010	SPEED_PROFILE	speedProfileNr	436	100000 down / 6000 up		SERVICE-Profil FIBER (ab Aug13)

						passiv)
1010	SPEED_PROFILE	speedProfileNr	244	max100000 down / 10000 up		SERVICE-Profil on-TDM & SA (ab Aug13 auch ADSL)
1010	SPEED_PROFILE	speedProfileNr	437	100000 down / 10000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	247	max100000 down / 20000 up		SERVICE-Profil COPPER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	438	100000 down / 20000 up		SERVICE-Profil FIBER (asymmetric) [Nov09]
1010	SPEED_PROFILE	speedProfileNr	447	70000 down / 70000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	289	max100000 down / 100000 up		SERVICE-Profil COPPER (1:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	448	100000 down / 100000 up (Business)		SERVICE-Profil FIBER
1010	SPEED_PROFILE	speedProfileNr	472	100000 down / 100000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	491	125000 down / 12500 up		SERVICE-Profil FIBER (10:1)
1010	SPEED_PROFILE	speedProfileNr	496	125000 down / 25000 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	408	125000 down / 125000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	473	150000 down / 15000 up		SERVICE-Profil FIBER (10:1)
1010	SPEED_PROFILE	speedProfileNr	474	150000 down / 30000 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	475	150000 down / 150000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	278	max200000 down / 20000 up		SERVICE-Profil COPPER (10:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	476	200000 down / 20000 up		SERVICE-Profil FIBER (10:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	276	max200000 down / 40000 up		SERVICE-Profil COPPER (5:1) [Mar15]
1010	SPEED_PROFILE	speedProfileNr	477	200000 down / 40000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	478	200000 down / 200000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	279	max250000 down / 25000 up		SERVICE-Profil

						COPPER (10:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	479	250000 down / 25000 up		SERVICE-Profil FIBER (10:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	280	max250000 down / 50000 up		SERVICE-Profil COPPER (5:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	480	250000 down / 50000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	481	250000 down / 250000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	281	max300000 down / 30000 up		SERVICE-Profil COPPER (10:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	492	300000 down / 30000 up		SERVICE-Profil FIBER (10:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	282	max300000 down / 60000 up		SERVICE-Profil COPPER (5:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	497	300000 down / 60000 up		SERVICE-Profil FIBER (5:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	409	300000 down / 300000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	283	max500000 down / 50000 up		SERVICE-Profil COPPER (10:1) [Jun15]
1010	SPEED_PROFILE	speedProfileNr	482	500000 down / 50000 up		SERVICE-Profil FIBER (10:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	277	max500000 down / 100000 up		SERVICE-Profil COPPER (5:1) [Mar15]
1010	SPEED_PROFILE	speedProfileNr	483	500000 down / 100000 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	484	500000 down / 500000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	485	1000000 down / 100000 up		SERVICE-Profil FIBER (10:1) [Nov13]
1010	SPEED_PROFILE	speedProfileNr	486	1000000 down / 200000 up		SERVICE-Profil FIBER (5:1)
1010	SPEED_PROFILE	speedProfileNr	487	1000000 down / 1000000 up		SERVICE-Profil FIBER (1:1)
1010	SPEED_PROFILE	speedProfileNr	0	ENABLING		Pseudo-SERVICE- Profil Streaming and Real Time
1014	LOV_OP_STATUS	opStatus	3	Open Pipe NA Max		

1014	LOV_OP_STATUS	opStatus	2	Open Pipe Manual		
1014	LOV_OP_STATUS	opStatus	1	Open Pipe Security		
1014	LOV_OP_STATUS	opStatus	4	Open Pipe LQS Max		
1014	LOV_OP_STATUS	opStatus	5	Open Pipe Risk		
1014	LOV_OP_STATUS	opStatus	6	Open Pipe Exception		
1014	LOV_OP_STATUS	opStatus	7	Open Pipe Measure		
1014	LOV_OP_STATUS	opStatus	8	Open Pipe NA Max High		
1050	LOV_AVERAGE_FLAG	averageFlag	0	The non-average qualif answer	The non-average qualif answer	
1050	LOV_AVERAGE_FLAG	averageFlag	1	The average qualif answer (strict address qualif)	The average qualif answer (strict address qualif)	
1050	LOV_AVERAGE_FLAG	averageFlag	2	The average qualif answer (fuzzy address qualif)	The average qualif answer (fuzzy address qualif)	
1051	LOV_OSI_RECOMMENDATION	bbrRecommendation	0	0 = na (not available)		
1051	LOV_OSI_RECOMMENDATION	bbrRecommendation	1	1 = BBR necessary ('broadband ready')		
1051	LOV_OSI_RECOMMENDATION	bbrRecommendation	2	2 = no BBR necessary		
1051	LOV_OSI_RECOMMENDATION	bbrRecommendation	3	3 = VDSL installation ok		
1051	LOV_OSI_RECOMMENDATION	bbrRecommendation	4	4 = stability at risk		
1052	LOV_LINE_STATE	lineState	1	active		
1052	LOV_LINE_STATE	lineState	2	inactive		
1052	LOV_LINE_STATE	lineState	3	planned		
1052	LOV_LINE_STATE	lineState	4	all		
1054	LOV_POTENTIAL_AVAILABLE	potentialAvailable	0	Not Potential Available	Not Potential Available	
1054	LOV_POTENTIAL_AVAILABLE	potentialAvailable	1	Potential Available	Potential Available	
1055	LOV_BB_RESOURCE_TYPE	resourceType	1	Port		
1055	LOV_BB_RESOURCE_TYPE	resourceType	2	Copper		
1055	LOV_BB_RESOURCE_TYPE	resourceType	3	WARP Port		
1060	LOV_NA_FAILURE_TYPE	NAFailuretype	0	OK	OK	
1060	LOV_NA_FAILURE_TYPE	NAFailuretype	2	NOK	NOK	
1060	LOV_NA_FAILURE_TYPE	NAFailuretype	11	OK – ADSL NAmix in Case of Port mismatch and CPE OK	OK – ADSL NAmix in Case of Port mismatch and CPE OK	
1060	LOV_NA_FAILURE_TYPE	NAFailuretype	12	OK – ADSL NAmix in Case of Port mismatch and CPE nok / na	OK – ADSL NAmix in Case of Port mismatch and CPE nok / na	
1060	LOV_NA_FAILURE_TYPE	NAFailuretype	13	OK – ADSL NAmix in Case of Port match but CPE na / nok	OK – ADSL NAmix in Case of Port match but CPE na / nok	
1060	LOV_NA_FAILURE_TYPE	NAFailuretype	14	OK – ADSL NAmix in Case of Port match, CPE match but the upgrooming is missing ...	OK – ADSL NAmix in Case of Port match, CPE match but the upgrooming is missing ...	

1061	LOV_BB_PSD_CLASS	stabilityClass	10	Spec_VDSL2_12a		Feb12 (R425)
1061	LOV_BB_PSD_CLASS	stabilityClass	20	Spec_VDSL2_17a		Feb12 (R425)
1061	LOV_BB_PSD_CLASS	stabilityClass	22	Spec_VDSL2_17a_rtx		VDSL Stabilisierung BBMar10
1061	LOV_BB_PSD_CLASS	stabilityClass	30	Spec_VDSL2_8b		Feb12 (R425)
1061	LOV_BB_PSD_CLASS	stabilityClass	32	Spec_VDSL2_8b_rtx		VDSL Stabilisierung BBMar10
1061	LOV_BB_PSD_CLASS	stabilityClass	40	Spec_VDSL2_FAST		neuer Eintrag für Nov15
1062	LOV_FIBER_LINE_STATE	fiberLineState	1	CONNECTED		
1062	LOV_FIBER_LINE_STATE	fiberLineState	2	AVAILABLE		
1062	LOV_FIBER_LINE_STATE	fiberLineState	3	PLANNED		
1062	LOV_FIBER_LINE_STATE	fiberLineState	4	NOT CONNECTED		Nov10-Release
1062	LOV_FIBER_LINE_STATE	fiberLineState	5	NO INHOUSE INSTALLATION		Nov12-Release
1062	LOV_FIBER_LINE_STATE	fiberLineState	6	CONNECTED (COPA)	Connected (CoPa)	Mai13-Release
1062	LOV_FIBER_LINE_STATE	fiberLineState	7	CONNECTED (ALO)	Connected (ALO)	Mai13-Release
1062	LOV_FIBER_LINE_STATE	fiberLineState	8	CONNECTED (LSG)	Connected (LSG)	Aug14-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	1	1 - BEP.NOK		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	2	2 - BEP.Planned		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	3	3 - BEP.Planned		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	4	4 - BEP.Ready		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	5	5 - OTO.Only		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	6	6 - OTO.Planned		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	7	7 - OTO.Planned		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	8	8 - OTO-Ready		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	9	9 - Fiber.Ready		Nov10-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	10	10 - OTO.Assigned-SLA.Sequential		Nov12-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	11	11 - OTO.Assigned-Parallel		FEB 2013 Upgrade DB
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	12	12 - Fiber.Ready-KoPA		Mai2013-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	13	13 - Fiber.Ready-ALO		Mai2013-Release
1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	14	14 - Fiber.Ready-CustomSolution		August2014- Release

1063	LOV_FIBER_BUSINESS_STATE	fiberBusinessState	99	99 - OTO.Assigned-Appointment		FEB 2013 Upgrade DB
1064	LOV_DSLAM_TYPE	dslamType	1	ASAM		
1064	LOV_DSLAM_TYPE	dslamType	2	ISAM		
1064	LOV_DSLAM_TYPE	dslamType	3	CAN		
1064	LOV_DSLAM_TYPE	dslamType	4	BCAN		
1065	LOV_ACCESS_SPEED_CHANGED	accessSpeedChange	1	unchanged		
1065	LOV_ACCESS_SPEED_CHANGED	accessSpeedChange	2	increased		
1065	LOV_ACCESS_SPEED_CHANGED	accessSpeedChange	3	decreased		
1066	LOV_SERVICE_MIX		1	7		
1066	LOV_SERVICE_MIX		2	8		
1066	LOV_SERVICE_MIX		3	10		
1066	LOV_SERVICE_MIX		4	13		
1066	LOV_SERVICE_MIX		5	13,9		
1066	LOV_SERVICE_MIX		6	13,9,12		
1066	LOV_SERVICE_MIX		7	13,12		
1066	LOV_SERVICE_MIX		8	14		
1066	LOV_SERVICE_MIX		9	14,12		
1066	LOV_SERVICE_MIX		10	18		
1066	LOV_SERVICE_MIX		11	18,9		
1066	LOV_SERVICE_MIX		12	18,9,12		
1066	LOV_SERVICE_MIX		13	18,12		
1066	LOV_SERVICE_MIX		14	110,9		
1066	LOV_SERVICE_MIX		15	110,9,12		
1066	LOV_SERVICE_MIX		16	110,9,12,100		
1066	LOV_SERVICE_MIX		17	110,9,100		
1066	LOV_SERVICE_MIX		18	110,12		
1066	LOV_SERVICE_MIX		19	110,12,100		
1066	LOV_SERVICE_MIX		20	110,100		
1066	LOV_SERVICE_MIX		21	120,9		
1066	LOV_SERVICE_MIX		22	120,9,12		
1066	LOV_SERVICE_MIX		23	120,9,12,100		
1066	LOV_SERVICE_MIX		24	120,9,100		
1066	LOV_SERVICE_MIX		25	120,12		
1066	LOV_SERVICE_MIX		26	120,12,100		
1066	LOV_SERVICE_MIX		27	120,100		
1066	LOV_SERVICE_MIX		28	220,9,12,100		

1066	LOV_SERVICE_MIX		29	420,101		
1066	LOV_SERVICE_MIX		30	910,9		
1066	LOV_SERVICE_MIX		31	910,9,12		
1066	LOV_SERVICE_MIX		32	910,9,12,100		
1066	LOV_SERVICE_MIX		33	910,9,100		
1066	LOV_SERVICE_MIX		34	910,12		
1066	LOV_SERVICE_MIX		35	910,12,100		
1066	LOV_SERVICE_MIX		36	910,100		
1066	LOV_SERVICE_MIX		37	110,300		
1066	LOV_SERVICE_MIX		38	120,300		
1066	LOV_SERVICE_MIX		39	830,9,12,100		
1066	LOV_SERVICE_MIX		40	840,12,100		
1070	LOV_UP_PREPARATION	Up Preparation	1	normal	normal	
1070	LOV_UP_PREPARATION	Up Preparation	2	limited copper available at this location	limited copper available at this location	
1101	LOV_NF_OBJECT	object	1	BBCS-Order		
1101	LOV_NF_OBJECT	object	2	BBCS-Installation Ticket		
1101	LOV_NF_OBJECT	object	3	BBCS-Access Ticket TT		
1101	LOV_NF_OBJECT	object	4	BBCS-Connectivity TT		
1101	LOV_NF_OBJECT	object	5	FA-Order		
1101	LOV_NF_OBJECT	object	6	FA-TT		
1101	LOV_NF_OBJECT	object	7	FA-Clarification T		
1101	LOV_NF_OBJECT	object	8	Information Request		
1101	LOV_NF_OBJECT	object	9	Voice Business		
1101	LOV_NF_OBJECT	object	10	COPA Order		
1101	LOV_NF_OBJECT	object	11	COPA Trouble Ticket		
1101	LOV_NF_OBJECT	object	12	Change Ticket		
1101	LOV_NF_OBJECT	object	13	Network Customer Notification		
1101	LOV_NF_OBJECT	object	15	ALO Order		DB Upgrade MAY14
1101	LOV_NF_OBJECT	object	16	L1 Solution/Provider		DB Upgrade AUG14
1101	LOV_NF_OBJECT	object	17	ALO Trouble Ticket		DB Upgrade NOV14
1102	LOV_NF_IR_OBJECT_TYPE	objectType	1	ISPPlannedOutage		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	2	ProKu		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	3	DexImport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	4	DexExport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	5	CPEReport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	6	NetworkCustomerNotificationChangeReport		

1102	LOV_NF_IR_OBJECT_TYPE	objectType	7	CustomerReport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	8	PartnerFileImport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	9	PartnerFileExport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	10	NetworkCustomerNotificationReschedulingReport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	11	NetworkCustomerNotificationAbortReport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	12	NetworkCustomerNotificationDelayReport		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	13	FtxCoverage		
1102	LOV_NF_IR_OBJECT_TYPE	objectType	14	DexAcceptance		
1103	LOV_NF_IR_OBJECT_STATE	objectState	1	ENTERED	N	
1103	LOV_NF_IR_OBJECT_STATE	objectState	2	CHECKED	N	
1103	LOV_NF_IR_OBJECT_STATE	objectState	3	PROCESSING	N	
1103	LOV_NF_IR_OBJECT_STATE	objectState	4	EXECUTED	N	
1103	LOV_NF_IR_OBJECT_STATE	objectState	5	COMPLETED	Y	
1103	LOV_NF_IR_OBJECT_STATE	objectState	6	EXCEPTION	Y	
1103	LOV_NF_IR_OBJECT_STATE	objectState	7	ABORTED	Y	
1104	LOV_NF_IR_OBJECT_STEP	objectStep	1	requestValidated		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	2	aihOK		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	3	poFileReceived		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	4	mvPOfileDone		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	5	aihTimeout		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	6	aihNACK		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	7	mvPOfileFailed		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	8	manualAbort		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	9	fileReceived		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	10	fileValid		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	11	fileInvalid		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	12	processingSuccess		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	13	processingException		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	14	manualAbort		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	15	uploaded		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	16	imported		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	17	created		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	18	exported		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	19	downloaded		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	20	rejected		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	21	transferred		
1104	LOV_NF_IR_OBJECT_STEP	objectStep	22	accepted		

1104	LOV_NF_IR_OBJECT_STEP	objectStep	23	processingStart		
1105	LOV_NF_ACTIVATOR	activator	1	Order		
1105	LOV_NF_ACTIVATOR	activator	2	Grooming		
1105	LOV_NF_ACTIVATOR	activator	3	Voice Business		
1105	LOV_NF_ACTIVATOR	activator	4	EventNotification		
1106	LOV_NF_INITIATOR	initiator	1	ISP		
1106	LOV_NF_INITIATOR	initiator	2	SCS		
1106	LOV_NF_INITIATOR	initiator	3	SCS-FF		
1106	LOV_NF_INITIATOR	initiator	4	COPA		
1106	LOV_NF_INITIATOR	initiator	5	PARTNER		
1107	LOV_NF_EVENT	notificationEvent	1	Classical Notification		
1107	LOV_NF_EVENT	notificationEvent	2	Order Notification		
1108	LOV_CLASS_OF_SERVICE	classOfService	0	Off		
1108	LOV_CLASS_OF_SERVICE	classOfService	1	On		
1110	LOV_FIBER_ACCESS_SPEED_STATE	LineSegmentState	1	Connected		
1110	LOV_FIBER_ACCESS_SPEED_STATE	LineSegmentState	2	Disconnected		
1110	LOV_FIBER_ACCESS_SPEED_STATE	LineSegmentState	3	Planned		
1111	LOV_FIBER_PORT_STATE	Portstate	1	Connected		
1111	LOV_FIBER_PORT_STATE	Portstate	2	Available		
1111	LOV_FIBER_PORT_STATE	Portstate	3	Planned		
1112	LOV_ACCESS_PROTOCOL	ACCESS_PROTOCOL	1	ADSL		
1112	LOV_ACCESS_PROTOCOL	ACCESS_PROTOCOL	2	SDSL		
1112	LOV_ACCESS_PROTOCOL	ACCESS_PROTOCOL	3	VDSL		
1112	LOV_ACCESS_PROTOCOL	ACCESS_PROTOCOL	4	A/SDSL		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	997	11 down / 11 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	212	max 4000 down / 600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	221	16000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	10	600 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	214	4000 down / 600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	225	20000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	216	max 12000 down / 2000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	218	12000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	222	max 16000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	7	2400 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	202	max 3500 down / 300 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	204	max 15000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	201	max 2000 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	200	max 300 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	404	300 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	239	max500 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	275	500 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	205	max 1000 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	403	1000 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	410	1000 down / 100 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	240	max2000 down / 200 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	241	max2000 down / 200 up (PAYG)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	449	2000 down / 200 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	248	max2000 down / 400 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	450	2000 down / 400 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	249	max2000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	451	2000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	8	300 down / 300 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	211	max 600 down / 600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	217	600 down / 600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedPr	250	max2500 down / 250 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	452	2500 down / 250 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	251	max2500 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	453	2500 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	252	max2500 down / 2500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	454	2500 down / 2500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	27	4400 down / 400 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	203	max5000 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	233	max5000 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	411	5000 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	253	max5000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	455	5000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	254	max5000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	456	5000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	213	max6000 down / 600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	215	6000 down / 600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	219	1200 down / 1200 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	220	1800 down / 1800 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	228	2000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	439	2000 down / 2000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	255	max8000 down / 800 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	457	8000 down / 800 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	256	max8000 down / 1600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	458	8000 down / 1600 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	257	max8000 down / 8000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	459	8000 down / 8000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	229	4000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	440	4000 down / 4000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	209	max10000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	412	10000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	258	max10000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	413	10000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	259	max10000 down / 10000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	460	10000 down / 10000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	414	15000 down / 500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	415	15000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	207	max15000 down / 1500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	461	15000 down / 1500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	416	15000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	261	max15000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	417	15000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	262	max15000 down / 15000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	462	15000 down / 15000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	224	max 16000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	223	16000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	210	max 20000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	418	20000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	230	max20000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	419	20000 down / 2000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	231	20000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	420	20000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	263	max20000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	463	20000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	232	20000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	234	6000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	441	6000 down / 6000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	264	max20000 down / 20000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	464	20000 down / 20000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	421	25000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	422	25000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	265	max25000 down / 2500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	465	25000 down / 2500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	423	25000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	266	max25000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	424	25000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	425	25000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	235	8000 down / 8000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	442	8000 down / 8000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	236	10000 down / 10000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	443	10000 down / 10000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	444	20000 down / 20000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	284	max25000 down / 25000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	466	25000 down / 25000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	426	30000 down / 1000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	427	30000 down / 2000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	237	max30000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	238	max30000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	401	30000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	428	30000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	429	30000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	267	max30000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	430	30000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	285	max30000 down / 30000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	445	30000 down / 30000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	467	30000 down / 30000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	260	max40000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	488	40000 down / 4000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	272	max40000 down / 8000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	493	40000 down / 8000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	286	max40000 down / 40000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	405	40000 down / 40000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	431	50000 down / 3000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	242	max50000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	432	50000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	433	50000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	246	max50000 down / 10000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	402	50000 down / 10000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	434	50000 down / 10000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	287	max50000 down / 50000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	446	50000 down / 50000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	468	50000 down / 50000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	270	max60000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	489	60000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	273	max60000 down / 12000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	494	60000 down / 12000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	406	60000 down / 60000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	268	max75000 down / 7500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	469	75000 down / 7500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	269	max75000 down / 15000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	470	75000 down / 15000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	471	75000 down / 75000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	271	max80000 down / 8000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	490	80000 down / 8000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	274	max80000 down / 16000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	495	80000 down / 16000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	288	max80000 down / 80000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	407	80000 down / 80000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	435	100000 down / 5000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	436	100000 down / 6000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	244	max100000 down / 10000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	437	100000 down / 10000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	247	max100000 down / 20000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	438	100000 down / 20000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	447	70000 down / 70000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	289	max100000 down / 100000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	448	100000 down / 100000 up (Business)		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	472	100000 down / 100000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	491	125000 down / 12500 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	496	125000 down / 25000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	408	125000 down / 125000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	473	150000 down / 15000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	474	150000 down / 30000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	475	150000 down / 150000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	278	max200000 down / 20000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	476	200000 down / 20000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	276	max200000 down / 40000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	477	200000 down / 40000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	478	200000 down / 200000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	279	max250000 down / 25000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	479	250000 down / 25000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	280	max250000 down / 50000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	480	250000 down / 50000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	481	250000 down / 250000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	281	max300000 down / 30000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	492	300000 down / 30000 up		

		ofileNr				
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	282	max300000 down / 60000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	497	300000 down / 60000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	409	300000 down / 300000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	283	max500000 down / 50000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	482	500000 down / 50000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	277	max500000 down / 100000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	483	500000 down / 100000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	484	500000 down / 500000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	485	1000000 down / 100000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	486	1000000 down / 200000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	487	1000000 down / 1000000 up		
1133	LOV_SPEED_PROFILE_SERVICE	serviceSpeedProfileNr	0	ENABLING		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	998	"Fair use Speed" up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	154	5000-8000 down / 400-1000 up (inaktives Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	24	4400 down / 500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	18	600 down / 600 up (n/a)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	32	15000 down / 5000 up (never used)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	155	150-300 down / 50-100 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	701	150 down / 150 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	601	300 down / 50 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	15	300-600 down / 50-100 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	702	300 down / 300 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	1	600 down / 100 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	602	600-800 down / 50-100 up		

		ofileNr		(ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	703	500 down / 500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	704	500 down / 500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	705	600 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	706	600 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	707	600 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	340	1200 down / 200 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	2	1200 down / 200 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	603	1200-2400 down / 100-200 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	11	2400 down / 200 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	342	4000 down / 300 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	147	300 down / 200-300 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	127	600 down / 280-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	131	1200 down / 280-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	135	2400 down / 280-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	604	2400-3000 down / 100-200 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	345	3000 down / 400 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	22	3000 down / 400 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	39	2000-4000 down / 300-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	605	3000-4000 down / 200-300 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	23	3600 down / 400-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	606	3600-5000 down / 200-300 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	25	4000 down / 400-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	347	4400 down / 500 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	607	4000-6000 down / 200-300 up		

		ofileNr		(ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	151	4400 down / 400-500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	608	4400-7000 down / 300-500 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	348	5000 down / 500 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	26	5000 down / 500 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	37	4000 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	346	4000 down / 600 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	609	5000-8000 down / 300-500 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	610	6000-9000 down / 400-600 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	349	6000 down / 600 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	38	6000 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	183	6700 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	708	1000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	709	1000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	710	1000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	19	1200 down / 1200 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	319	1200 down / 1200 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	20	1800 down / 1800 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	320	1800 down / 1800 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	711	2000 down / 2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	712	2000 down / 2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	713	2000 down / 2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	33	2000-2800 down / 100-300 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	34	5000 down / 400-600 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	158	8000 down / 400 up (Not-Profile)		

		ofileNr				
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	168	5000-8000 down / 500-600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	157	8000 down / 600 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	152	8000 down / 600-1000 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	611	8000-11000 down / 600-800 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	160	5000-8000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	28	8000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	301	8000 down / 1000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	175	10000 down / 600 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	612	10000-13000 down / 600-800 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	169	5000-10000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	55	10000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	176	12000 down / 600 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	42	12000 down / 600-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	714	4000 down / 4000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	715	4000 down / 4000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	716	4000 down / 4000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	613	12000-15000 down / 600-800 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	622	14000-17000 down / 600-800 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	161	5000-12000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	156	12000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	310	12000 down / 1000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	614	12000-15000 down / 600-1000 up (ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	177	15000 down / 600 up (Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	623	15000-18000 down / 600-800 up		

		ofileNr		(ADSL2+)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	162	5000-15000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	29	15000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	303	15000 down / 1000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	153	15000 down / 1000-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	163	5000-15000 down / 500-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	31	15000 down / 2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	184	5000-18000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	178	18000 down / 1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	621	300-18750 down / 50-1016 up (ADSL2+ / Not-Profile)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	170	5000-18000 down / 500-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	56	18000 down / 2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	304	15000 down / 2000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	311	18000 down / 2000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	500	5000-20000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	164	5000-20000 down / 500-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	227	20000 down / 2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	309	20000 down / 2000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	305	20000 down / 5000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	165	5000-20000 down / 500-5000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	30	20000 down / 5000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	717	6000 down / 6000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	718	6000 down / 6000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	306	20000 down / 6000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	171	5000-20000 down / 500-6000 up		

		ofileNr				
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	41	20000 down / 6000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	501	5000-22000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	179	5000-22000 down / 500-4000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	60	22000 down / 4000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	312	22000 down / 4000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	182	5000-22000 down / 500-5000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	63	22000 down / 5000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	172	5000-22000 down / 500-6000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	57	22000 down / 6000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	313	22000 down / 6000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	502	5000-25000 down / 500-1000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	503	5000-25000 down / 500-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	719	8000 down / 8000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	720	8000 down / 8000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	307	25000 down / 10000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	721	10000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	722	10000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	723	12000 down / 12000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	724	14000 down / 14000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	725	16000 down / 16000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	726	18000 down / 18000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	727	20000 down / 20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	226	5000-25000 down / 500-5000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	166	5000-25000 down / 500-10000		

		ofileNr		up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	35	25000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	504	5000-30000 down / 500-2000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	186	5000-30000 down / 500-7000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	308	30000 down / 10000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	167	5000-30000 down / 500-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	36	30000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	505	5000-33000 down / 500-4000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	180	5000-33000 down / 500-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	61	33000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	506	5000-40000 down / 500-5000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	173	5000-40000 down / 500-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	58	40000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	507	5000-44000 down / 500-7000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	181	5000-44000 down / 500-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	62	44000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	174	5000-50000 down / 500-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	59	50000 down / 10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	314	50000 down / 10000 up (CIS & LAN-I)		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	187	5000-50000 down / 500-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	508	5000-60000 down / 5000-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	188	5000-60000 down / 500-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	189	5000-70000 down / 500-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	190	5000-80000 down / 500-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr	513	5000-80000 down / 5000-20000		

		ofileNr		up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	514	5000-80000 down / 5000-25000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	801	5000-80000 down / 5000-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	802	5000-80000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	509	5000-90000 down / 5000-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	511	5000-90000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	515	5000-90000 down / 5000-25000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	803	5000-100000 down / 5000-10000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	510	5000-100000 down / 5000-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	804	5000-100000 down / 5000-15000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	512	5000-100000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	805	5000-100000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	516	5000-100000 down / 5000-25000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	51	100000 down / 100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	806	5000-120000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	807	5000-120000 down / 5000-25000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	808	5000-120000 down / 5000-30000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	809	5000-140000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	810	5000-140000 down / 5000-25000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	811	5000-140000 down / 5000-30000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	812	5000-160000 down / 5000-20000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	813	5000-160000 down / 5000-30000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	814	5000-160000 down / 5000-40000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	815	5000-180000 down / 5000-30000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr	816	5000-180000 down / 5000-35000		

		ofileNr		up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	817	5000-180000 down / 5000-40000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	818	5000-200000 down / 5000-30000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	819	5000-200000 down / 5000-40000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	820	5000-200000 down / 5000-50000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	821	5000-250000 down / 5000-40000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	822	5000-250000 down / 5000-50000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	823	5000-250000 down / 5000-60000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	824	5000-250000 down / 5000-70000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	825	5000-300000 down / 5000-50000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	826	5000-300000 down / 5000-60000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	827	5000-300000 down / 5000-70000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	828	5000-300000 down / 5000-80000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	829	5000-350000 down / 5000-50000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	830	5000-350000 down / 5000-60000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	831	5000-350000 down / 5000-70000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	832	5000-350000 down / 5000-80000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	833	5000-350000 down / 5000-90000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	834	5000-400000 down / 5000-60000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	835	5000-400000 down / 5000-70000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	836	5000-400000 down / 5000-80000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	837	5000-400000 down / 5000-90000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	838	5000-400000 down / 5000- 100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr ofileNr	839	5000-450000 down / 5000-70000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedPr	840	5000-450000 down / 5000-80000		

		ofileNr		up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	841	5000-450000 down / 5000-90000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	842	5000-450000 down / 5000-100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	843	5000-450000 down / 5000-120000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	844	5000-500000 down / 5000-80000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	845	5000-500000 down / 5000-90000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	846	5000-500000 down / 5000-100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	847	5000-500000 down / 5000-120000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	848	5000-550000 down / 5000-90000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	849	5000-550000 down / 5000-100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	850	5000-550000 down / 5000-120000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	851	5000-550000 down / 5000-140000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	852	5000-600000 down / 5000-100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	853	5000-600000 down / 5000-120000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	854	5000-600000 down / 5000-140000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	855	5000-600000 down / 5000-150000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	856	5000-600000 down / 5000-160000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	857	5000-650000 down / 5000-100000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	858	5000-650000 down / 5000-120000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	800	500-1000000 down / 500-1000000 up		
1134	LOV_SPEED_PROFILE_ACCESS	accessSpeedProfileNr	64	1000000 down / 1000000 up		
1201	LOV_MESSAGE_TYPE	messageType	1	GV01		
1201	LOV_MESSAGE_TYPE	messageType	2	GV02		
1201	LOV_MESSAGE_TYPE	messageType	3	GV03		
1201	LOV_MESSAGE_TYPE	messageType	4	GV04		
1201	LOV_MESSAGE_TYPE	messageType	5	GV05		
1201	LOV_MESSAGE_TYPE	messageType	6	GV06		

1201	LOV_MESSAGE_TYPE	messageType	11	GV11		
1201	LOV_MESSAGE_TYPE	messageType	12	GV12		
1201	LOV_MESSAGE_TYPE	messageType	14	GV14		
1201	LOV_MESSAGE_TYPE	messageType	15	GV15		
1201	LOV_MESSAGE_TYPE	messageType	16	GV16		
1201	LOV_MESSAGE_TYPE	messageType	17	GV17		
1201	LOV_MESSAGE_TYPE	messageType	25	GV25		
1201	LOV_MESSAGE_TYPE	messageType	37	GV37		
1201	LOV_MESSAGE_TYPE	messageType	173	GV173		
1201	LOV_MESSAGE_TYPE	messageType	174	GV174		
1202	LOV_APV_MESSAGE_GROUP_STATE	groupState	1	OPEN	The Voice-GV was opened	
1202	LOV_APV_MESSAGE_GROUP_STATE	groupState	2	DELAYED	Portshortage	
1202	LOV_APV_MESSAGE_GROUP_STATE	groupState	3	DONE	The Voice-GV was done.	
1204	LOV_APV_MESSAGE_GROUP_TYPE	groupType	1	With BB		
1204	LOV_APV_MESSAGE_GROUP_TYPE	groupType	2	Without BB		
1300	LOV_EQUIPPED_DATE_QUALITY		1	1 = 99.9%		
1300	LOV_EQUIPPED_DATE_QUALITY		2	2 = 99%		
1300	LOV_EQUIPPED_DATE_QUALITY		3	3 = 97%		
1300	LOV_EQUIPPED_DATE_QUALITY		4	4 = 95%		
1300	LOV_EQUIPPED_DATE_QUALITY		5	5 = 75%		
1300	LOV_EQUIPPED_DATE_QUALITY		98	98 = end date is over but it is not usable at the moment		
1300	LOV_EQUIPPED_DATE_QUALITY		99	99 = abort of a building process		
1301	LOV_BUSINESS_TYPE	BusinessType	1	New		
1301	LOV_BUSINESS_TYPE	BusinessType	2	Relocation		
1301	LOV_BUSINESS_TYPE	BusinessType	3	Product Change		
1302	LOV_DSL_FULFILLMENT_TYPE		1	ATM		
1302	LOV_DSL_FULFILLMENT_TYPE		2	EAP		
1302	LOV_DSL_FULFILLMENT_TYPE		3	WARP		
1302	LOV_DSL_FULFILLMENT_TYPE		9	FulfillmentStop		
1302	LOV_DSL_FULFILLMENT_TYPE		10	FulfillmentWait		
1303	LOV_DSL_FULFILLMENT_STATUS		1	OK		
1303	LOV_DSL_FULFILLMENT_STATUS		2	1st-way_Stop		
1303	LOV_DSL_FULFILLMENT_STATUS		3	2nd-way_Stop		

1303	LOV_DSL_FULFILLMENT_STATU S		4	2nd-way_Wait		
1304	LOV_PRODUCT_OFFERING		1	PO_BBCS_ON_TDM		
1304	LOV_PRODUCT_OFFERING		2	PO_BBCS_STANDALONE		
1304	LOV_PRODUCT_OFFERING		3	PO_DBC		
1304	LOV_PRODUCT_OFFERING		4	PO_RAMPLUS_STANDALONE		
1304	LOV_PRODUCT_OFFERING		5	PO_WARP_STANDALONE		
1308	LOV_TIME_SLOT_TYPES		40	Daily new		
1308	LOV_TIME_SLOT_TYPES		30	Halfday new		
1308	LOV_TIME_SLOT_TYPES		10	Two Hours new		
1308	LOV_TIME_SLOT_TYPES		20	Four Hours		
1309	LOV_NC_SERVICE_NAME	NC Service Name	1	Service Provider KoPa v1 CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	2	Service Provider KoPa v2 CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	3	Service Provider ALO CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	4	Service Provider ALO v1 CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	5	Service Provider ALO v1+ CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	6	Service Provider ALO v2 CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	7	All-IP Basic Connectivity CFS Instance		
1309	LOV_NC_SERVICE_NAME	NC Service Name	8	unknown		
1309	LOV_NC_SERVICE_NAME	NC Service Name	9	Service Provider KoPa v1+ CFS Instance		
1310	LOV_UMSA_SERVICE_NAME	UMSA Service Name	1	COPALayer1		
1310	LOV_UMSA_SERVICE_NAME	UMSA Service Name	2	ALO		
1310	LOV_UMSA_SERVICE_NAME	UMSA Service Name	3	BBCS-F		
1310	LOV_UMSA_SERVICE_NAME	UMSA Service Name	4	unknown		
1311	LOV_NC_UMSA_USE_CASE	NC UMSA use case	1	UC.0	UC.0 - OMDF Connector was not changed	
1311	LOV_NC_UMSA_USE_CASE	NC UMSA use case	2	UC.1	UC.1 - if only OMDF Connector has been changed	
1311	LOV_NC_UMSA_USE_CASE	NC UMSA use case	3	UC.2.A	UC.2.A - OMDF has been changed but this change in the same room with relation to the old XMDF. Non frozen OMDF-XMDF Relation exists and old patch length is bigger or equal to needed new patch length.	

1311	LOV_NC_UMSA_USE_CASE	NC UMSA use case	4	UC.2.M	UC.2.M - OMDF has been changed. This change is in the same room without relation to the old XMDF. Old patch length is strictly smaller to needed new patch length; or non frozen OMDF-XMDF Relation does not exist	
1311	LOV_NC_UMSA_USE_CASE	NC UMSA use case	5	UC.3	UC.3 - OMDF has been changed. This change is in the different room in the same central office.(Where Room is defined via Room/Zone of OMDF device and Central Office is found through objects hierarchy)	
1311	LOV_NC_UMSA_USE_CASE	NC UMSA use case	6	UC.4	UC.4 - OMDF has been changed. New OMDF is in the different central office. (Where central Office is found through objects hierarchy)	
1312	LOV_UMSA_NEEDED_INTERACTION	UMSA needed interaction	1	no partner interaction needed		
1312	LOV_UMSA_NEEDED_INTERACTION	UMSA needed interaction	2	partner has to disconnect the old and recreate the new connection		
1312	LOV_UMSA_NEEDED_INTERACTION	UMSA needed interaction	3	partner has to recreate existing connection of patchtype 3		
1313	LOV_MIGRATION_REASON	Migration Reason	45	Software Upgrade CAN		
1313	LOV_MIGRATION_REASON	Migration Reason	51	Cu@WARP		Belassen wie vorher. Falls gewünscht kann dies ja wieder geändert werden
1313	LOV_MIGRATION_REASON	Migration Reason	60	Vectoring AccessNode		
1313	LOV_MIGRATION_REASON	Migration Reason	63	Port Relocation / Rewiring		
1313	LOV_MIGRATION_REASON	Migration Reason	64	Leitungsverkürzung mit Überführungsrelevanz		
1313	LOV_MIGRATION_REASON	Migration Reason	65	FTTS/B Leitungsverkürzung		
1313	LOV_MIGRATION_REASON	Migration Reason	66	FTTS/B UMSA mit Leitungsverkürzung		
1313	LOV_MIGRATION_REASON	Migration Reason	69	FTTS/B UMSA		
1313	LOV_MIGRATION_REASON	Migration Reason	968	FTTS/B Leitungsverkürzung , UMSA mit Leitungsverkürzung		
1313	LOV_MIGRATION_REASON	Migration Reason	994	UMSA Reports ULL TED-Letters (Interface U2)		
1313	LOV_MIGRATION_REASON	Migration Reason	995	Leitungswechsel ULL/FA		
1316	LOV_CUSTOMER_NOTIFICATION_TYPE	WSG DB 9.7	1	All IP Vecotring CAN Exchange Confirmation	AIIP_VECTORING_CAN_EXCHANGE_CONFIRMATION	Feb14-Release
1316	LOV_CUSTOMER_NOTIFICATION_TYPE	WSG DB 9.7	2	All IP Vecotring CAN Exchange Aborted	AIIP_VECTORING_CAN_EXCHANGE_ABORTED	Feb14-Release

1316	LOV_CUSTOMER_NOTIFICATION_TYPE	WSG DB 9.7	3	All IP Vecotring CAN Exchange Info	AIIP_VECTORING_CAN_EXCHANGE_INFO	Feb14-Release
1316	LOV_CUSTOMER_NOTIFICATION_TYPE	WSG DB 9.7	4	All IP FAN Exchange Confirmation	AIIP_FAN_EXCHANGE_CONFIRMATION	Feb14-Release
1316	LOV_CUSTOMER_NOTIFICATION_TYPE	WSG DB 9.7	5	Copper at Warp Info	CU_WARP_INFO	Feb14-Release
1316	LOV_CUSTOMER_NOTIFICATION_TYPE	WSG DB 9.7	6	Copper at Warp Closed	CU_WARP_CLOSED	Feb14-Release
1317	LOV_ALO_SF_SLA		1	Basic	BASIC	
1317	LOV_ALO_SF_SLA		2	Express	EXPRESS	
1317	LOV_ALO_SF_SLA		3	Express - Swisscom Fault	Express - Swisscom Fault	
1318	LOV_ALO_SA_SLA		1	Standard	STANDARD	
1318	LOV_ALO_SA_SLA		3	OnDemand	EVENT-BASED	
1319	LOV_NF_ALO_OBJECT_TYPE		81	Create ALO	ALO_CREATE	
1319	LOV_NF_ALO_OBJECT_TYPE		82	Disconnect ALO	ALO_DISCONNECT	
1319	LOV_NF_ALO_OBJECT_TYPE		85	Change ALO	ALO_SRV_CHANGE	
1320	LOV_ALO_ORDER_TYPE		81	Create ALO	ALO_CREATE	
1320	LOV_ALO_ORDER_TYPE		82	Disconnect ALO	ALO_DISCONNECT	
1320	LOV_ALO_ORDER_TYPE		85	Change ALO	ALO_SRV_CHANGE	
1321	LOV_NF_ORDER_STATE		1	ENTERED		
1321	LOV_NF_ORDER_STATE		2	HOLDING		
1321	LOV_NF_ORDER_STATE		3	PRE_REJECTED		
1321	LOV_NF_ORDER_STATE		4	CHECKED		
1321	LOV_NF_ORDER_STATE		5	PROCESSING		
1321	LOV_NF_ORDER_STATE		6	ACCEPTED		
1321	LOV_NF_ORDER_STATE		7	EXECUTED		
1321	LOV_NF_ORDER_STATE		8	REJECTED		
1321	LOV_NF_ORDER_STATE		9	DELAYED		
1321	LOV_NF_ORDER_STATE		10	CANCEL PENDING		
1321	LOV_NF_ORDER_STATE		11	CANCELLED		
1321	LOV_NF_ORDER_STATE		12	PLANNED		
1321	LOV_NF_ORDER_STATE		13	COMPLETED		
1321	LOV_NF_ORDER_STATE		14	EXCEPTION		
1321	LOV_NF_ORDER_STATE		15	PARKED		
1321	LOV_NF_ORDER_STATE		16	ONSITE_PENDING		
1322	LOV_NF_TT_STATE		1	ENTERED		
1322	LOV_NF_TT_STATE		2	REJECTED		
1322	LOV_NF_TT_STATE		3	CHECKED		
1322	LOV_NF_TT_STATE		4	PROCESSING		
1322	LOV_NF_TT_STATE		5	INWORK		

1322	LOV_NF_TT_STATE		6	CLOSED		
1322	LOV_NF_TT_STATE		7	CANCELLED		
1324	LOV_EQUIPPED_DATE_EVENT_T YPE	equipped date event type	1	TargetDateChange		
1324	LOV_EQUIPPED_DATE_EVENT_T YPE	equipped date event type	2	ValidityClassException		
1326	LOV_COPA_ZONE_CONTRACT_R ES		0	0 - Not Used	0	
1326	LOV_COPA_ZONE_CONTRACT_R ES		1	SC - Swisscom	SC	
1326	LOV_COPA_ZONE_CONTRACT_R ES		2	F - Fremd (Cooperation Partner)	F	
1326	LOV_COPA_ZONE_CONTRACT_R ES		3	FP - Fremd PoP	FP	
1327	LOV_ALO_TT_STATE		1	ENTERED	New	
1327	LOV_ALO_TT_STATE		3	CHECKED		
1327	LOV_ALO_TT_STATE		4	PROCESSING		
1327	LOV_ALO_TT_STATE		5	INWORK	InProgress	
1327	LOV_ALO_TT_STATE		6	CLOSED	Closed	
1327	LOV_ALO_TT_STATE		7	CANCELLED	Cancelled	
1327	LOV_ALO_TT_STATE		8	RESOLVED	Resolved	
1327	LOV_ALO_TT_STATE		10	PENDING	Pending	
1327	LOV_ALO_TT_STATE		14	EXCEPTION		
1327	LOV_ALO_TT_STATE		15	PRE_REJECTED	PreRejected	
1327	LOV_ALO_TT_STATE		16	CANCEL PENDING	Cancel pending	
1328	LOV_ALO_TT_PROBLEM_CODE1		400	Physical Access	1600	
1329	LOV_ALO_TT_PROBLEM_CODE2		800	ALO	4606	
1330	LOV_ALO_TT_PROBLEM_CODE3		900	No Signal	5631	
1330	LOV_ALO_TT_PROBLEM_CODE3		901	Interruption	5627	
1330	LOV_ALO_TT_PROBLEM_CODE3		902	Performance Problem	5635	
1330	LOV_ALO_TT_PROBLEM_CODE3		903	LinkTest NOK	5642	
1331	LOV_ALO_TT_RESOLUTION_COD E_1		101	OTO	7000	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_COD E_1		102	BEP OMDF	7002	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_COD E_1		103	Breakout Cable	7003	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_COD E_1		104	BEP	7004	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_COD E_1		105	OMDF	7008	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_COD E_1		106	XMDF	7012	WSG 9.10

1331	LOV_ALO_TT_RESOLUTION_CODE_1		107	OMDF-OTO	7017	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_CODE_1		108	Patch Cable	7020	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_CODE_1		109	Repair not possible	7024	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_CODE_1		110	No Fault Clearance	7025	WSG 9.10
1331	LOV_ALO_TT_RESOLUTION_CODE_1		111	Inhouse Cable	7042	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		201	Fibre Cut	8001	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		202	Attenuation	8002	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		203	Incorrect Splice	8003	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		204	Wrong Position Connected	8004	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		205	Defective mounting	8013	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		206	Damage	8045	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		207	Customer never reached	8063	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		208	Everything ok	8069	WSG 9.10
1332	LOV_ALO_TT_RESOLUTION_CODE_2		209	Not Responsible	8193	Kü
1332	LOV_ALO_TT_RESOLUTION_CODE_2		210	OK from Customer	8067	Kü
1333	LOV_ALO_TT_RESOLUTION_CODE_3		300	Temporary Solution	9001	WSG 9.10
1333	LOV_ALO_TT_RESOLUTION_CODE_3		0	Undefined	0	WSG 9.10
1334	LOV_ALO_PATCH_TYPE		1	V1	1	
1334	LOV_ALO_PATCH_TYPE		2	V2	2	
1334	LOV_ALO_PATCH_TYPE		11	V1plus	1	
1335	LOV_ALO_TT_ITSM_INCIDENT_STATE		1	queued	queued	
1335	LOV_ALO_TT_ITSM_INCIDENT_STATE		2	openActivate	openActivate	
1335	LOV_ALO_TT_ITSM_INCIDENT_STATE		3	openActivate.onsite	openActivate.onsite	
1335	LOV_ALO_TT_ITSM_INCIDENT_STATE		4	deferred.scheduled	deferred.scheduled	
1335	LOV_ALO_TT_ITSM_INCIDENT_STATE		5	cleared	cleared	

1335	LOV_ALO_TT_ITSM_INCIDENT_S TATE		6	closed	closed	
1335	LOV_ALO_TT_ITSM_INCIDENT_S TATE		7	closed.cancelled	closed.cancelled	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		1	infrastructure change created	1000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		2	on site action required	2000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		3	order approval	3000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		4	registration approval	4000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		5	supplier delivery	5000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		6	returned by support contact	6000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		7	third-party vendor action required	7000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		8	client action required	8000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		9	infrastructure change	9000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		10	requirement	10000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		11	future improvements	11000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		12	Original incident pending	12000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		13	deferred by customer	13000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		14	incident monitoring	14000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		15	customer resubmission required	15000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		16	temporary corrective action	16000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		17	no further action required	17000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		19	automatic solution reported	19000	
1336	LOV_ALO_TT_ITSM_INCIDENT_S TATE_REASON		20	no causal CI anymore	20000	
1337	LOV_ALO_TT_VISITCONDUCTED		1	Yes	Yes	
1337	LOV_ALO_TT_VISITCONDUCTED		2	No	No	
1338	LOV_NF_ALO_TT_STATE		1	ENTERED	New	
1338	LOV_NF_ALO_TT_STATE		3	CHECKED		
1338	LOV_NF_ALO_TT_STATE		4	PROCESSING		

1338	LOV_NF_ALO_TT_STATE		5	INWORK	InProgress	
1338	LOV_NF_ALO_TT_STATE		6	CLOSED	Closed	
1338	LOV_NF_ALO_TT_STATE		7	CANCELLED	Cancelled	
1338	LOV_NF_ALO_TT_STATE		8	RESOLVED	Resolved	
1338	LOV_NF_ALO_TT_STATE		10	PENDING	Pending	
1338	LOV_NF_ALO_TT_STATE		14	EXCEPTION		
1338	LOV_NF_ALO_TT_STATE		15	PRE_REJECTED	PreRejected	
1338	LOV_NF_ALO_TT_STATE		16	CANCEL PENDING	Cancel pending	
1339	LOV_NF_ALO_TT_OBJECT_TYPE		1	ALO		
1340	LOV_QUALIFICATION_HINT		100	Only WARP Equipment for this product allowed		
1340	LOV_QUALIFICATION_HINT		200	ReturnSpeedAtNok		Nov15-Release
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	1	Start Virtual Order preprocessing		Virtual Order has been created -> preprocess virtual order.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	2	Start Virtual Order processing		Virtual Order is ready to be processed -> call GetSrvStatus and evaluate 1st Way rule.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	3	Start 1st Way Order preprocessing		Real 1st Way order has been created -> preprocess real 1st Way order.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	4	Start APV processing		Order has been passed to ApvManager -> waiting for 1st Way completion.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	5	Call getXdsIPort		getXdsIPort-Request has been initiated --> wait for getXdsIPort completion.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	6	Start 2nd Way Order preprocessing		Real 2nd Way order has been created -> preprocess real 2nd Way order.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	7	Start 2nd Way (MPM) processing		Order has been passed to Java for sending to MPM -> wait for MPM completion.
1341	LOV_EXPECTED_NEXT_UPDATE_STEP	Describes the expected next update steps.	8	Start New 2nd Way processing		Order has been passed to Java for sending to Cope/NC -> wait for New 2nd Way completion.

1342	LOV_TARGET_DATETIME		1	NOW	Current Date/Time	
1342	LOV_TARGET_DATETIME		2	ENTRY_DATETIME	Entry Date/Time of the (virtual) order	
1342	LOV_TARGET_DATETIME		3	ENTRY_DATETIME + 1 Working Day	Entry Date/Time of the (virtual) order + 1 Working Day	
1342	LOV_TARGET_DATETIME		4	ACTI_DATE/ENTRY_DATE	CWD (Date only)	
1342	LOV_TARGET_DATETIME		5	ACTI_DATE/ENTRY_DATE + 1 Day	CWD (Date only) + 1 Day	
1342	LOV_TARGET_DATETIME		6	ACTI_DATETIME_VOICE	Voice Activation/Deactivation Date/Time	
1342	LOV_TARGET_DATETIME		7	SZF_END_DATETIME	Timeslot End Date/Time	
1342	LOV_TARGET_DATETIME		8	ADOPTION_START_DATETIME	Adoption Start Date/Time (time when the Voice deactivation takes place)	
1343	LOV_OVERDUE_SEVERITY	Describes the severity in case of overdue.	1	High		
1343	LOV_OVERDUE_SEVERITY	Describes the severity in case of overdue.	2	Medium		
1343	LOV_OVERDUE_SEVERITY	Describes the severity in case of overdue.	3	Low		
1344	LOV_OVERDUE_ORDER_CATEGORY	Describes the severity in case of overdue.	1	adoption		
1345	LOV_COPA_BUSINESS_TYPE		1	New		
1345	LOV_COPA_BUSINESS_TYPE		11	SynchOrder		
1346	LOV_COPA_USE_CASE		1	ASR Driven		
1346	LOV_COPA_USE_CASE		2	FUF Driven		
1347	LOV_FIB_UPDATE		1	With FIBUpdate		Juni15-Release
1347	LOV_FIB_UPDATE		2	Without FIBUpdate		Juni15-Release
1347	LOV_FIB_UPDATE		3	Only FIBUpdate		Juni15-Release
1348	LOV_ALO_BUSINESS_TYPE		1	New		
1348	LOV_ALO_BUSINESS_TYPE		3	Product Change		
1349	LOV_ORDER_TAG		100	Manually resolved "Clean Order Check Failed"-Exception		Nov15-Release
1349	LOV_ORDER_TAG		101	Automatically resolved "Clean Order Check Failed"-Exception		Nov15-Release
1350	LOV_CPE_CAPABILITY		0	no		Feb16-Release
1350	LOV_CPE_CAPABILITY		1	yes		Feb16-Release
1350	LOV_CPE_CAPABILITY		2	yes, but SFP needed		Feb16-Release
1351	LOV_STABILITY_CLASS		1	bad stability/quality		Feb16-Release
1351	LOV_STABILITY_CLASS		2	medium stability/quality		Feb16-Release
1351	LOV_STABILITY_CLASS		3	good stability/quality		Feb16-Release
1352	LOV_ATTAINABLE_ACTUAL_BITRATE_RATIO		1	Low Margin		Feb16-Release

1352	LOV_ATTAINABLE_ACTUAL_BITRATE_RATIO		2	High Margin		Feb16-Release
1353	LOV_BB_PORT_LINE_TYPE	WSG 9.4	0	na	na	
1353	LOV_BB_PORT_LINE_TYPE	WSG 9.4	1	ana	ana	
1353	LOV_BB_PORT_LINE_TYPE	WSG 9.4	2	dig	dig	
1353	LOV_BB_PORT_LINE_TYPE	WSG 9.4	3	combo	combo	
1353	LOV_BB_PORT_LINE_TYPE	WSG 9.4	4	sym	sym	
1501	LOV_WSG_REGIONS	region	1	West		
1501	LOV_WSG_REGIONS	region	2	Central		
1501	LOV_WSG_REGIONS	region	3	East		
1501	LOV_WSG_REGIONS	region	4	South		
1502	LOV_BILLING_ACTION	billingAction	1	not billed		
1502	LOV_BILLING_ACTION	billingAction	2	ready for billing		
1502	LOV_BILLING_ACTION	billingAction	3	billing cancelled		
1502	LOV_BILLING_ACTION	billingAction	4	billing submitted		
1503	LOV_BILLING_ZONE	billingZone	1	City		
1503	LOV_BILLING_ZONE	billingZone	2	Region		
1503	LOV_BILLING_ZONE	billingZone	3	Rest		
1503	LOV_BILLING_ZONE	billingZone	11	FIBER_Default_Billing_Zone		
2001	LOV_VALID_ULL_TECH_REQUESTS		1	1		ADSL
2001	LOV_VALID_ULL_TECH_REQUESTS		2	2		VDSL2
2001	LOV_VALID_ULL_TECH_REQUESTS		3	3		SDSL
2001	LOV_VALID_ULL_TECH_REQUESTS		4	4		HDSL
2001	LOV_VALID_ULL_TECH_REQUESTS		5	5		HDSL2B1Q
2001	LOV_VALID_ULL_TECH_REQUESTS		6	6		HDSL2CAP
2001	LOV_VALID_ULL_TECH_REQUESTS		7	7		POTS
2001	LOV_VALID_ULL_TECH_REQUESTS		8	8		ISDN
2001	LOV_VALID_ULL_TECH_REQUESTS		9	9		ADSL2+
2001	LOV_VALID_ULL_TECH_REQUESTS		10	1,2		ADSL,VDSL2
2001	LOV_VALID_ULL_TECH_REQUESTS		11	1,2,9		ADSL,VDSL2,ADSL2+
2001	LOV_VALID_ULL_TECH_REQUESTS		12	1,9		ADSL,ADSL2+
2001	LOV_VALID_ULL_TECH_REQUESTS		13	2,9		VDSL2,ADSL2+

	TS					
2002	LOV_IR3_CHECKLISTE		7	Please provide additional information concerning the reject of this TAL-request according to the following PTS comment.		
2003	LOV_ORDER_TYPE_ULL		1	ACCESS_CREATE	ACCESS_CREATE	
2003	LOV_ORDER_TYPE_ULL		2	ACCESS_MODIFY	ACCESS_MODIFY	
2003	LOV_ORDER_TYPE_ULL		3	ACCESS_DISCON	ACCESS_DISCON	
2003	LOV_ORDER_TYPE_ULL		4	ULL_GETSTATUS	GET_SRV_STATUS	
2004	LOV_ULL_BUSINESS_CASE		1	Create		
2004	LOV_ULL_BUSINESS_CASE		2	Modify		
2004	LOV_ULL_BUSINESS_CASE		3	Disconnect		
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	51	51 - 1st level	1st level	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	52	52 - 2nd level	2nd level	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	53	53 - on site	on site	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	54	54 - others	others	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	702	702 - suspend customer	suspend customer	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	703	703 - resumed	resumed	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	701	701 - overdue	overdue	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	58	58 - done - service available	done - service available	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	59	59 - cable	cable	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	60	60 - dispatching	dispatching	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	61	61 - appointment arranged	appointment arranged	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	62	62 - appointment arranged outside SLA	appointment arranged outside SLA	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	705	705 - suspend diagnose	suspend diagnose	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	64	64 - closed - confirmed	closed - confirmed	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	65	65 - closed - not confirmed	closed - not confirmed	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	69	69 - cancel appointment	cancel appointment	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	70	70 - message from PTS/ISP	message from PTS/ISP	
3001	LOV_TT_PROGRESS_COMMENT_CODE	progeSSComme ntCode	71	71 - cancel failed	message from livenet	

	_CODE	ntCode				
3001	LOV_TT_PROGRESS_COMMENT_CODE	progressCommentCode	706	706 - message to PTS/ISP	message to PTS/ISP	
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	200	200 - Customer-Fault-FF, Problem solved		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	201	201 - Customer-Fault-FF, CE-Problem, Problem not solved		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	202	202 - Customer-Fault-Remote, Problem solved		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	203	203 - Swisscom-Fault-Cross Connection		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	204	204 - Swisscom-Fault-Configuration		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	205	205 - Swisscom-Fault-Hardware		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	206	206 - Swisscom-Fault-Software		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	207	207 - Swisscom O.K.		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	250	250 - BBBS-Access Swisscom Fault Infrastructure		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	251	251 - BBBS-Access Swisscom O.K.		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	252	252 - BBBS-Access Swisscom-Fault-Configuration		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	253	253 - BBBS-Access Swisscom-Fault-Hardware		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	254	254 - BBBS Access Swisscom-Fault Cross Connection		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	255	255 - BBBS Access Customer Fault not solved		
3002	LOV_TT_RESPONSE_COMMENT_CODE	responseCommentCode	0	0 - Internal use		
3010	LOV_TT_KIND	ERROR CATEGORY	500	500 - Unknown		
3010	LOV_TT_KIND	ERROR CATEGORY	501	501 - xDSL Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	502	502 - SF-VIP		CRQ000000302359
3010	LOV_TT_KIND	ERROR CATEGORY	503	503 - Real Time Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	504	504 - Unknown Error		Standard -> Unknown Error gem. Liste 180.3 - Aug'09
3010	LOV_TT_KIND	ERROR CATEGORY	505	505 - Streaming Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	507	507 - Splitter Installation Ticket		

3010	LOV_TT_KIND	ERROR CATEGORY	508	508 - Set-Top-Box affected		
3010	LOV_TT_KIND	ERROR CATEGORY	509	509 - Additional Settop Box		
3010	LOV_TT_KIND	ERROR CATEGORY	510	510 - Timas 510 BBS-Express		
3010	LOV_TT_KIND	ERROR CATEGORY	512	512 - Coord. troubleshooting		Coordinated onsite troubleshooting
3010	LOV_TT_KIND	ERROR CATEGORY	513	513 - Shutdown not successful		
3010	LOV_TT_KIND	ERROR CATEGORY	515	515 - Mobile Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	516	516 - Real Time (Business) Trouble Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	517	517 - Fibre InstallationTicket		von "VOBB (Business) Installation Ticket" umbenannt für März-Rel. '09 (Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	519	519 - ADSL Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	521	521 - VDSL Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	523	523 - SDSL Installation Ticket		
3010	LOV_TT_KIND	ERROR CATEGORY	525	525 - Proactive Troubleshooting		
3010	LOV_TT_KIND	ERROR CATEGORY	527	527 - WIMAX Installation		
3010	LOV_TT_KIND	ERROR CATEGORY	529	529 - Streaming ADSL -> VDSL Install		neuer Eintrag für Jun09
3010	LOV_TT_KIND	ERROR CATEGORY	531	531 - DSL ready		
3010	LOV_TT_KIND	ERROR CATEGORY	534	534 - VDSL Self Install failed		
3010	LOV_TT_KIND	ERROR CATEGORY	535	535 - Router-Change		CRQ000000195032
3010	LOV_TT_KIND	ERROR CATEGORY	539	539 - Unknown Error		neuer Eintrag für Jun09
3010	LOV_TT_KIND	ERROR CATEGORY	540	540 - 2nd Level Analysis		Anpassung Eintrag für Jun11 (alt:Internet Recaller)
3010	LOV_TT_KIND	ERROR CATEGORY	541	541 - No Signal		
3010	LOV_TT_KIND	ERROR CATEGORY	542	542 - No Connection		
3010	LOV_TT_KIND	ERROR CATEGORY	543	543 - Interruptions		

3010	LOV_TT_KIND	ERROR CATEGORY	544	544 - Performance Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	545	545 - Unknown		
3010	LOV_TT_KIND	ERROR CATEGORY	546	546 - No Signal		
3010	LOV_TT_KIND	ERROR CATEGORY	547	547 - No Connection		
3010	LOV_TT_KIND	ERROR CATEGORY	548	548 - Interruptions		
3010	LOV_TT_KIND	ERROR CATEGORY	549	549 - Performance Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	550	550 - Home Installation Quality		
3010	LOV_TT_KIND	ERROR CATEGORY	551	551 - No Signal		
3010	LOV_TT_KIND	ERROR CATEGORY	552	552 - No Connection		
3010	LOV_TT_KIND	ERROR CATEGORY	553	553 - Interruptions		
3010	LOV_TT_KIND	ERROR CATEGORY	554	554 - Performance Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	555	555 - Freeze 1a/3 Streaming down		
3010	LOV_TT_KIND	ERROR CATEGORY	557	557 - Freeze 2 Streaminglimited		
3010	LOV_TT_KIND	ERROR CATEGORY	559	559 - No Set-Top-Box connectivity		
3010	LOV_TT_KIND	ERROR CATEGORY	560	560 - Installation durch Techniker		INC480759
3010	LOV_TT_KIND	ERROR CATEGORY	561	561 - SA-VIP BBS		CRQ000000302362
3010	LOV_TT_KIND	ERROR CATEGORY	564	564 - SCS Line Quality Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	571	571 - Line Quality Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	579	579 - Unknown		neuer Eintrag für Jun09
3010	LOV_TT_KIND	ERROR CATEGORY	580	580 - TIMAS Pilot Routing		von 580 - Access problems auf 580 - TIMAS Pilot Routing, 02.07.2013 J.Meier
3010	LOV_TT_KIND	ERROR CATEGORY	581	581 - Missing Digit Socket		neuer Eintrag für März-Rel. '09 (Anf. Proj. GGate)
3010	LOV_TT_KIND	ERROR CATEGORY	585	585 - Fibre Access Problems		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)

3010	LOV_TT_KIND	ERROR CATEGORY	586	586 - Fibre Service Problems		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	587	587 - Fibre Special		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	588	588 - Fibre Access Problems		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	589	589 - Fibre Service Problems		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	590	590 - Fibre Special		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	591	591 - Fibre Access Problems		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	592	592 - Fibre Service Problems		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	593	593 - Fibre Special		neuer Eintrag für März-Rel. '09 (Anf. Proj. FTTH)
3010	LOV_TT_KIND	ERROR CATEGORY	595	595 - All-IP DBC (copper)		neuer Eintrag für All-IP DBC Nov '09
3010	LOV_TT_KIND	ERROR CATEGORY	596	596 - All-IP FBC (fiber)		neuer Eintrag für All-IP FBC Mrz '10
3010	LOV_TT_KIND	ERROR CATEGORY	600	600 - Unknown		
3010	LOV_TT_KIND	ERROR CATEGORY	601	601 - Performance Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	602	602 - PTS/Swisscom onsite resol. needed		
3010	LOV_TT_KIND	ERROR CATEGORY	610	610 - Unknown		
3010	LOV_TT_KIND	ERROR CATEGORY	611	611 - Performance Problems		
3010	LOV_TT_KIND	ERROR CATEGORY	612	612 - PTS/Swisscom onsite resol. needed		
3010	LOV_TT_KIND	ERROR CATEGORY	640	640 - GA Internet		CRQ000000183880
3010	LOV_TT_KIND	ERROR CATEGORY	641	641 - GA Internet Onsite		CRQ000000164089 , CRQ000000218654
3010	LOV_TT_KIND	ERROR CATEGORY	650	650 - GA Stream TV		CRQ000000183883
3010	LOV_TT_KIND	ERROR CATEGORY	651	651 - StreamTV No Signal		CRQ000000164090
3010	LOV_TT_KIND	ERROR CATEGORY	701	701 - SCSStreaming Dir.Triage After TechChange		Umbenennung von BWTV... zu

						SCSTV... Nov'09
3010	LOV_TT_KIND	ERROR CATEGORY	702	702 - SCSStreaming Direct Triage After OSI		Umbenennung von BWTV... zu SCSTV... Nov'09
3010	LOV_TT_KIND	ERROR CATEGORY	705	705 - OSI Streaming Move		
3010	LOV_TT_KIND	ERROR CATEGORY	706	706 - OSI Streaming VDSL- Upgrade		
3010	LOV_TT_KIND	ERROR CATEGORY	707	707 - Alternativ BB Sat		
3010	LOV_TT_KIND	ERROR CATEGORY	708	708 - Alternativ BB WIMAX		
3010	LOV_TT_KIND	ERROR CATEGORY	709	709 - Alternativ BB HSPA		
3010	LOV_TT_KIND	ERROR CATEGORY	721	721 - Home Network Services		
3010	LOV_TT_KIND	ERROR CATEGORY	730	730 - All-IP FBC (fibre) special		neuer Eintrag für All-IP FBC Nov '09
3010	LOV_TT_KIND	ERROR CATEGORY	731	731 - BBFS-F (fibre) special		neuer Eintrag für BBFS-F Nov'09
3010	LOV_TT_KIND	ERROR CATEGORY	900	900 - No Signal		
3010	LOV_TT_KIND	ERROR CATEGORY	901	901 - No Connections		
3010	LOV_TT_KIND	ERROR CATEGORY	902	902 - Performance		
3010	LOV_TT_KIND	ERROR CATEGORY	903	903 - Interruptions		
3010	LOV_TT_KIND	ERROR CATEGORY	910	910 - Linktest failed		Gemäss Vorschlag Vaterlaus/Seltmann
3011	LOV_NOTIFICATION_TYPE	endUserNotificat ionType	1	None	None	
3011	LOV_NOTIFICATION_TYPE	endUserNotificat ionType	2	SMS	Sms	
3011	LOV_NOTIFICATION_TYPE	endUserNotificat ionType	3	Email	Email	
3012	LOV_ICA_ANALYSIS_STATE		0	Finished		
3012	LOV_ICA_ANALYSIS_STATE		1	Cancel		
3012	LOV_ICA_ANALYSIS_STATE		2	Abort		
3012	LOV_ICA_ANALYSIS_STATE		3	Error		
3012	LOV_ICA_ANALYSIS_STATE		4	ErrorCAN		
3012	LOV_ICA_ANALYSIS_STATE		5	Measuring		
3012	LOV_ICA_ANALYSIS_STATE		6	NotAvailable		
3013	LOV_ICA_ANALYSIS_TYPE		1	LQD		
3013	LOV_ICA_ANALYSIS_TYPE		2	SELT		
3014	LOV_ICA_PROBLEM_CODE		1	BridgeTap		

3014	LOV_ICA_PROBLEM_CODE		2	Degraded Contact		
3014	LOV_ICA_PROBLEM_CODE		3	Missing Splitter		
3014	LOV_ICA_PROBLEM_CODE		4	Missing Splitter on alarm system		
3014	LOV_ICA_PROBLEM_CODE		5	External Interference detected		
3014	LOV_ICA_PROBLEM_CODE		6	Intermittent contact		
3014	LOV_ICA_PROBLEM_CODE		7	Loop unbalanced		
3014	LOV_ICA_PROBLEM_CODE		8	Untwisted in-house wiring		
3014	LOV_ICA_PROBLEM_CODE		9	Time varying noise (crosstalk and RFI)		
3014	LOV_ICA_PROBLEM_CODE		10	CPE interoperability problem		
3014	LOV_ICA_PROBLEM_CODE		11	Black-listed CPE		
3014	LOV_ICA_PROBLEM_CODE		17	Abnormal crosstalk		
3014	LOV_ICA_PROBLEM_CODE		19	BridgeTap on overhead line		
3014	LOV_ICA_PROBLEM_CODE		20	Rogue Line		
3014	LOV_ICA_PROBLEM_CODE		21	network element configuration issue	CONF	
3014	LOV_ICA_PROBLEM_CODE		22	CPE silent	CPS	
3014	LOV_ICA_PROBLEM_CODE		23	CPE failed	CPF	
3014	LOV_ICA_PROBLEM_CODE		24	connection status down	CSD	
3014	LOV_ICA_PROBLEM_CODE		25	inflex, actual rate smaller than planned	INFL	
3014	LOV_ICA_PROBLEM_CODE		26	CPE silent and/or configuration issue on the line and/or line is interrupted.	CPCO	
3014	LOV_ICA_PROBLEM_CODE		27	CPE silent because of loss of power	CPSP	
3014	LOV_ICA_PROBLEM_CODE		28	CPE silent because of loss of signal	CPSS	
3014	LOV_ICA_PROBLEM_CODE		29	CPE silent because of initialization failure	CPSC	
3014	LOV_ICA_PROBLEM_CODE		30	CPE silent because of loss of frame.	CPSF	
3014	LOV_ICA_PROBLEM_CODE		99	Other unknown (not mapped) impact		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		0	no problem		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		10	DSL_BBR: Bridge Tap or Degraded Contact causes resynchs and/or reduction of bandwidth		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		11	DSL_BBR Bridge Tap or Degraded Contact causes instabilities (CV/SES and possible resynchs)		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		15	DSL_BBR: Bridge Tap or Degraded Contact causes reduction of bandwidth and possibly resynchs; potential HD-TV		
3015	LOV_ICA_ACCESS_PROBLEM_TY		16	DSL_BBR: Bridge Tap or Degraded Contact causes		

	PE			instabilities and a reduction of bandwidth; potential HD-TV		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		20	DSL_Missing-Splitter possibly causes resynchs; CV/SES ok		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		21	DSL_Missing-Splitter possibly causes resynchs; CV/SES nok		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		30	DSL_unknown: Resynchs without ICA problem; no TV service		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		31	DSL_unknown: Instabilities (CV/SES and possibly resynchs) without ICA problem; no TV service		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		40	DSL_unknown: Resynchs without ICA problem; TV service		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		41	DSL_unknown: Instabilities (CV/SES and possibly resynchs) without ICA problem; TV service		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		90	Logical error - no findings		
3015	LOV_ICA_ACCESS_PROBLEM_TY PE		99	Line with OP-Status "manual" or configured with a flex-profile		
3016	LOV_ICA_PROBLEM_DETECTED		0	No problem detected		
3016	LOV_ICA_PROBLEM_DETECTED		1	Problem detected, but without impact on bandwidth or stability		
3016	LOV_ICA_PROBLEM_DETECTED		2	Problem detected, with impact on attainable bitrate		
3016	LOV_ICA_PROBLEM_DETECTED		3	Problem detected, with impact on stability		
3016	LOV_ICA_PROBLEM_DETECTED		4	Problem detected, with impact on attainable bitrate and stability		
3016	LOV_ICA_PROBLEM_DETECTED		99	No problem detected but unstable line		
3019	LOV_EXCHANGE_TYPE	Exchange Type	1	Hardware	5801	
3019	LOV_EXCHANGE_TYPE	Exchange Type	2	Firmware	5802	
3020	LOV_COMMUNICATION_CHANNEL	Communication Channel	1	email	Communication-Channel-email	
3020	LOV_COMMUNICATION_CHANNEL	Communication Channel	2	centralprint	Communication-Channel-centralprint	
3020	LOV_COMMUNICATION_CHANNEL	Communication Channel	3	sms	Communication-Channel-sms	
3021	LOV_CT_STATE	CT State	1	ENTERED	entered	
3021	LOV_CT_STATE	CT State	3	CANCEL PENDING	cancel pending	
3021	LOV_CT_STATE	CT State	4	PROCESSING	processing	
3021	LOV_CT_STATE	CT State	5	MODIFY PENDING	modify pending	
3021	LOV_CT_STATE	CT State	6	CLOSED	closed	
3021	LOV_CT_STATE	CT State	7	CANCELLED	cancelled	

3021	LOV_CT_STATE	CT State	8	REJECTED	rejected	
3021	LOV_CT_STATE	CT State	9	COMPLETED	completed	
3021	LOV_CT_STATE	CT State	14	EXCEPTION	exception	
3022	LOV_CT_STATE_REASON	CT State Reason	0	-	-	
3022	LOV_CT_STATE_REASON	CT State Reason	1	No Longer Required	1000	
3022	LOV_CT_STATE_REASON	CT State Reason	2	Funding Not Available	2000	
3022	LOV_CT_STATE_REASON	CT State Reason	3	To Be Re-Scheduled	3000	
3022	LOV_CT_STATE_REASON	CT State Reason	4	Resources Not Available	4000	
3022	LOV_CT_STATE_REASON	CT State Reason	5	Successful	5000	
3022	LOV_CT_STATE_REASON	CT State Reason	6	Successful with Issues	6000	
3022	LOV_CT_STATE_REASON	CT State Reason	7	Unsuccessful	7000	
3022	LOV_CT_STATE_REASON	CT State Reason	8	Backed Out	8000	
3022	LOV_CT_STATE_REASON	CT State Reason	9	Final Review Complete	9000	
3022	LOV_CT_STATE_REASON	CT State Reason	10	Final Review Required	10000	
3022	LOV_CT_STATE_REASON	CT State Reason	11	Additional Coding Required	11000	
3022	LOV_CT_STATE_REASON	CT State Reason	12	Insufficient Task Data	12000	
3022	LOV_CT_STATE_REASON	CT State Reason	13	In Verification	13000	
3022	LOV_CT_STATE_REASON	CT State Reason	14	In Rollout	14000	
3022	LOV_CT_STATE_REASON	CT State Reason	15	Insufficient Change Data	15000	
3022	LOV_CT_STATE_REASON	CT State Reason	16	Schedule Conflicts	16000	
3022	LOV_CT_STATE_REASON	CT State Reason	17	In Development	17000	
3022	LOV_CT_STATE_REASON	CT State Reason	18	In Test	18000	
3022	LOV_CT_STATE_REASON	CT State Reason	19	In Build	19000	
3022	LOV_CT_STATE_REASON	CT State Reason	20	In Rollback	20000	
3022	LOV_CT_STATE_REASON	CT State Reason	21	In Documentation	21000	

3022	LOV_CT_STATE_REASON	CT State Reason	22	Vendor Purchase	22000	
3022	LOV_CT_STATE_REASON	CT State Reason	23	Support Group Communication	23000	
3022	LOV_CT_STATE_REASON	CT State Reason	24	Task Review	24000	
3022	LOV_CT_STATE_REASON	CT State Reason	25	Miscellaneous	25000	
3022	LOV_CT_STATE_REASON	CT State Reason	26	Future Enhancement	26000	
3022	LOV_CT_STATE_REASON	CT State Reason	27	Manager Intervention	27000	
3022	LOV_CT_STATE_REASON	CT State Reason	29	Assigned	29000	
3022	LOV_CT_STATE_REASON	CT State Reason	30	Built	30000	
3022	LOV_CT_STATE_REASON	CT State Reason	32	Automatically Closed	32000	
3022	LOV_CT_STATE_REASON	CT State Reason	33	Done	50000	
3022	LOV_CT_STATE_REASON	CT State Reason	34	Done With Error (PIR)	51000	
3022	LOV_CT_STATE_REASON	CT State Reason	35	Failed (PIR)	52000	
3022	LOV_CT_STATE_REASON	CT State Reason	36	Post Incident (PIR)	53000	
3022	LOV_CT_STATE_REASON	CT State Reason	37	Postponed (PIR)	54000	
3022	LOV_CT_STATE_REASON	CT State Reason	38	Cancelled (PIR)	55000	
3022	LOV_CT_STATE_REASON	CT State Reason	39	Additional Testing/Development required	60000	
3022	LOV_CT_STATE_REASON	CT State Reason	40	Maintenance Window not considered	61000	
3022	LOV_CT_STATE_REASON	CT State Reason	41	Leadtime too short for Change Management	62000	
3022	LOV_CT_STATE_REASON	CT State Reason	42	Leadtime too short for Implementation	63000	
3022	LOV_CT_STATE_REASON	CT State Reason	43	Not authorized Change	64000	
3023	LOV_CT_TYPE	CT Type	1	CPE Change		
3023	LOV_CT_TYPE	CT Type	2	Fiber Port Upgrade		
4001	LOV_WT_STATE	itState	1	ENTERED		
4001	LOV_WT_STATE	itState	2	REJECTED		
4001	LOV_WT_STATE	itState	3	CHECKED		
4001	LOV_WT_STATE	itState	4	PROCESSING		
4001	LOV_WT_STATE	itState	5	INWORK		

4001	LOV_WT_STATE	itState	6	CLOSED		
4001	LOV_WT_STATE	itState	7	CANCELLED		
4002	LOV_WT_TYPE	itOrderType	1	INSTALLATION		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	1	None		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	2	xDSL Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	3	Splitter Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	4	Streaming Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	8	Streaming Settop Box		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	5	Real Time Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	6	Mobile Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	9	ADSL Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	10	VDSL Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	11	SDSL Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	16	Pilot Bridge Tap		WSG 9.4 CE FTTH_Pilot removed
4003	LOV_ONSITE_SUPPORT	onsiteSupport	17	Streaming ADSL -> VDSL Install		WSG 9.4 CE FTTH_Pilot removed
4003	LOV_ONSITE_SUPPORT	onsiteSupport	18	Home Installation Quality		WSG 9.4 CE FTTH_Pilot removed
4003	LOV_ONSITE_SUPPORT	onsiteSupport	15	DSL ready		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	90	SAT Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	91	WiMax Installation		
4003	LOV_ONSITE_SUPPORT	onsiteSupport	92	HSPA Installation		
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	0	none	1,2,3,4,8,5,6,9,10,11,20,15	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	1	xDSL-Installation	4,5,9,10,11,20,15	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	4	Streaming Installation	1,2,3,4,8,5,9,10,11,15	Anforderung aus Golden Gate für Juni '09
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	7	Streaming + 2 Hours	4,8,9,10,11,20,15	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	11	Additional Settop Box	2,3,4,8,5,9,10,11,20,15,90	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	13	Additional PC 1	2,3,4,8,5,9,10,11,15,90	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	14	Additional PC 2	2,3,4,8,5,9,10,11,15,90	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	15	WLAN 1	2,3,4,8,5,9,10,11,15,90	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	16	WLAN 2	2,3,4,8,5,9,10,11,15,90	

4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	19	Printer-Sharing	2,3,4,8,5,9,10,11,15,90	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	21	Splitter-Installation	2,4,5,9,10,11,15	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	23	Additional PC 1 (Mobile Unlimited)	6	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	24	Additional PC 2 (Mobile Unlimited)	6	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	25	WLAN 1 (Mobile Unlimited)	6	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	26	WLAN 2 (Mobile Unlimited)	6	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	27	DSL ready	4,8,5,9,10,11,20,15,90	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	90	Grundversorgung Installation	90,91,92	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	91	Grundversorgung Reparatur	90,91,92	
4004	LOV_ADDITIONAL_INSTALLATION	additionalInstallationReq	92	Grundversorgung De-Installation	90,91,92	
4005	LOV_SELF_INSTALL	selfinstall	1	Y		
4005	LOV_SELF_INSTALL	selfinstall	2	N		
4006	LOV_MODEM_OWNER	cpeOwner	3	Unknown		
4006	LOV_MODEM_OWNER	cpeOwner	1	Swisscom		
4006	LOV_MODEM_OWNER	cpeOwner	2	Admin ISP		
4007	LOV_HW_DELIVERY_STATE	hwDeliveryState	1	unknown		
4007	LOV_HW_DELIVERY_STATE	hwDeliveryState	2	pending		
4007	LOV_HW_DELIVERY_STATE	hwDeliveryState	3	delivered		
4008	LOV_WT_AI_STATE	Additional Installation state	1	open	open	
4008	LOV_WT_AI_STATE	Additional Installation state	2	done	done	
5000	LOV_COPA_PATCH_TYPE		1	V1	1	
5000	LOV_COPA_PATCH_TYPE		2	V2	2	
5000	LOV_COPA_PATCH_TYPE		3	V3	3	
5000	LOV_COPA_PATCH_TYPE		11	V1plus	11	
5001	LOV_COPA_SF_SLA		1	Standard	Standard	
5001	LOV_COPA_SF_SLA		2	Express	Express	
5001	LOV_COPA_SF_SLA		3	Express - Swisscom Fault	Express - Swisscom Fault	
5002	LOV_COPA_ORDER_TYPE		3	Disconnect L1C	Disconnect L1C	
5002	LOV_COPA_ORDER_TYPE		51	Create incoming L1C (CoPa -> SCS)	Create incoming L1C (CoPa -> SCS)	
5002	LOV_COPA_ORDER_TYPE		52	SynchOrder	SynchOrder	
5002	LOV_COPA_ORDER_TYPE		61	Create Inhouse (SCS -> CoPa)	Create Inhouse (SCS -> CoPa)	

5002	LOV_COPA_ORDER_TYPE		55	Fiber Rental Request incoming (CoPa -> SCS)	Fiber Rental Request incoming (CoPa -> SCS)	
5002	LOV_COPA_ORDER_TYPE		65	Fiber Rental Request outgoing (SCS -> CoPa)	Fiber Rental Request outgoing (SCS -> CoPa)	
5003	LOV_COPA_ORDER_STATE		1	ENTERED	The new order was just entered in the WSG DB	
5003	LOV_COPA_ORDER_STATE		2	HOLDING	The order is waiting until the manual check is done	
5003	LOV_COPA_ORDER_STATE		3	PRE_REJECTED	The manual check failed	
5003	LOV_COPA_ORDER_STATE		4	CHECKED	All checks ok, order is ready for processing	
5003	LOV_COPA_ORDER_STATE		5	PROCESSING	The order was processed successfully	
5003	LOV_COPA_ORDER_STATE		6	ACCEPTED	The order is accepted	
5003	LOV_COPA_ORDER_STATE		7	EXECUTED	The order was executed by COPE	
5003	LOV_COPA_ORDER_STATE		8	REJECTED	The order was rejected by WFM	
5003	LOV_COPA_ORDER_STATE		10	CANCEL_PENDING	The order was cancelled by WFM	
5003	LOV_COPA_ORDER_STATE		11	CANCELLED	The order was cancelled	
5003	LOV_COPA_ORDER_STATE		13	COMPLETED	The order has completed	
5003	LOV_COPA_ORDER_STATE		14	EXCEPTION		
5003	LOV_COPA_ORDER_STATE		17	ABORTED	The order was aborted by WFM	
5004	LOV_NF_COPA_ORDER_STATE		1	ENTERED	The new order was just entered in the WSG DB	
5004	LOV_NF_COPA_ORDER_STATE		2	HOLDING	The order is waiting until the manual check is done	
5004	LOV_NF_COPA_ORDER_STATE		3	PRE_REJECTED	The manual check failed	
5004	LOV_NF_COPA_ORDER_STATE		4	CHECKED	All checks ok, order is ready for processing	
5004	LOV_NF_COPA_ORDER_STATE		5	PROCESSING	The order was processed successfully	
5004	LOV_NF_COPA_ORDER_STATE		6	ACCEPTED	The order is accepted	
5004	LOV_NF_COPA_ORDER_STATE		7	EXECUTED	The order is executed	
5004	LOV_NF_COPA_ORDER_STATE		8	REJECTED		
5004	LOV_NF_COPA_ORDER_STATE		11	CANCELLED	The order was cancelled	
5004	LOV_NF_COPA_ORDER_STATE		13	COMPLETED	The order has completed	
5004	LOV_NF_COPA_ORDER_STATE		14	EXCEPTION		
5004	LOV_NF_COPA_ORDER_STATE		17	ABORTED		
5005	LOV_NF_COPA_OBJECT_TYPE		3	DISCONNECT L1C		
5005	LOV_NF_COPA_OBJECT_TYPE		51	CREATE L1C (CoPa -> SCS)		
5005	LOV_NF_COPA_OBJECT_TYPE		52	CREATE Synch (CoPa -> SCS)		
5005	LOV_NF_COPA_OBJECT_TYPE		61	CREATE FIO (SCS -> CoPa)		
5005	LOV_NF_COPA_OBJECT_TYPE		55	FRR incoming (CoPa -> SCS)		
5005	LOV_NF_COPA_OBJECT_TYPE		65	FRR outgoing (SCS -> CoPa)		
5006	LOV_COPA_CPE_INSTALLATION		1	Yes	Yes	

5006	LOV_COPA_CPE_INSTALLATION		2	No	No	
5006	LOV_COPA_CPE_INSTALLATION		3	Remove	Remove	
5007	LOV_COPA_INVENTORY_STATE		1	Active	Active	
5007	LOV_COPA_INVENTORY_STATE		2	Preactive	Preactive	
5007	LOV_COPA_INVENTORY_STATE		3	Inactive	Inactive	
5008	LOV_COPA_ADDRESS_TYPE		2	Installation	Mandatory for Inhouse Connection, at least the last name must be specified (the address is already filled by the qualification and is read only)	
5008	LOV_COPA_ADDRESS_TYPE		4	Contact Customer	Mandatory for Inhouse Connection, at least the last name and phone must be specified	
5008	LOV_COPA_ADDRESS_TYPE		0	Land Lord		
5008	LOV_COPA_ADDRESS_TYPE		1	Facility Manager		
5008	LOV_COPA_ADDRESS_TYPE		3	Care Taker		
5008	LOV_COPA_ADDRESS_TYPE		5	Ko Pa	Recommended for Cross Connection, only last name and phone will be sent to the backend system.	
5008	LOV_COPA_ADDRESS_TYPE		6	FDA		
5009	LOV_COPA_OUTOFSLA_REASON		10	Appointment outside of SLA due to customer preference	Appointment outside of SLA due to customer preference	
5009	LOV_COPA_OUTOFSLA_REASON		50	Appointment outside of SLA caused by Installation Partner Swisscom	Appointment outside of SLA caused by Installation Partner Swisscom	
5009	LOV_COPA_OUTOFSLA_REASON		60	Appointment outside of SLA caused by Installation Partner KoPa	Appointment outside of SLA caused by Installation Partner KoPa	
5010	LOV_COPA_WORKINFO_CODE		10	Order Pending	Order Pending	
5010	LOV_COPA_WORKINFO_CODE		20	Customer not reached	Customer not reached	
5010	LOV_COPA_WORKINFO_CODE		30	Delay for technical reason	Delay for technical reason	
5010	LOV_COPA_WORKINFO_CODE		40	Cancel order not possible	Cancel order not possible	
5010	LOV_COPA_WORKINFO_CODE		50	Information from Partner/KoPa	Information from Partner/KoPa	
5010	LOV_COPA_WORKINFO_CODE		60	Question from Partner/KoPa	Question from Partner/KoPa	
5010	LOV_COPA_WORKINFO_CODE		70	Information from Swisscom	Information from Swisscom	
5011	LOV_COPA_COMPLETION_CODE		0	Fibre Ready / Installation completed - optical signal available (BReq_FIO_OPT-04)	Fibre Ready / Installation completed - optical signal available (BReq_FIO_OPT-04)	
5011	LOV_COPA_COMPLETION_CODE		10	Fibre not Ready / Installation completed - no optical signal available (BReq_FIO_OPT-04)	Fibre not Ready / Installation completed - no optical signal available (BReq_FIO_OPT-04)	
5011	LOV_COPA_COMPLETION_CODE		60	Abort order caused by faulty inventory (UC 60 - Abbruch)	Abort order caused by faulty inventory (UC 60 - Abbruch)	
5011	LOV_COPA_COMPLETION_CODE		61	Abort order by customer wish (UC 60 - Abbruch)	Abort order by customer wish (UC 60 - Abbruch)	
5011	LOV_COPA_COMPLETION_CODE		62	Abort order by landlord wish (UC 60 - Abbruch)	Abort order by landlord wish (UC 60 - Abbruch)	

5011	LOV_COPA_COMPLETION_CODE		63	Abort order due to other reasons (UC 60 - Abbruch)	Abort order due to other reasons (UC 60 - Abbruch)	
5011	LOV_COPA_COMPLETION_CODE		64	Abort order because installation location does not exist (UC 60 - Abbruch)	Abort order because installation location does not exist (UC 60 - Abbruch)	
5011	LOV_COPA_COMPLETION_CODE		65	Abort order because OTO is already present (UC 60 - Abbruch)	Abort order because OTO is already present (UC 60 - Abbruch)	
5011	LOV_COPA_COMPLETION_CODE		66	Customer not reachable for booking appointment (UC 66 - Kunde nicht erreicht)	Customer not reachable for booking appointment (UC 66 - Kunde nicht erreicht)	
5012	LOV_COPA_WFM_FIO_STATE		10	New	New	
5012	LOV_COPA_WFM_FIO_STATE		20	Waiting	Waiting	
5012	LOV_COPA_WFM_FIO_STATE		30	CustomerPending	CustomerPending	
5012	LOV_COPA_WFM_FIO_STATE		40	ReadyToClean	ReadyToClean	
5012	LOV_COPA_WFM_FIO_STATE		50	Clean	Clean	
5012	LOV_COPA_WFM_FIO_STATE		60	Ready	Ready	
5012	LOV_COPA_WFM_FIO_STATE		70	Forwarded	Forwarded	
5012	LOV_COPA_WFM_FIO_STATE		80	Assigned	Assigned	
5012	LOV_COPA_WFM_FIO_STATE		100	Suspended	Suspended	
5012	LOV_COPA_WFM_FIO_STATE		110	Acknowledged	Acknowledged	
5012	LOV_COPA_WFM_FIO_STATE		120	Rejected	Rejected	
5012	LOV_COPA_WFM_FIO_STATE		130	Accepted	Accepted	
5012	LOV_COPA_WFM_FIO_STATE		140	TripStarted	TripStarted	
5012	LOV_COPA_WFM_FIO_STATE		150	InWork	InWork	
5012	LOV_COPA_WFM_FIO_STATE		160	OnHold	OnHold	
5012	LOV_COPA_WFM_FIO_STATE		180	Completed	Completed	
5012	LOV_COPA_WFM_FIO_STATE		190	Canceled	Canceled	
5012	LOV_COPA_WFM_FIO_STATE		200	Closed	Closed	
5012	LOV_COPA_WFM_FIO_STATE		210	Aborted	Aborted	
5012	LOV_COPA_WFM_FIO_STATE		230	Pull	Pull	
5013	LOV_SAP_CONNECTOR_STATE	WSG 9.4	1	Connected	Connected	
5013	LOV_SAP_CONNECTOR_STATE	WSG 9.4	2	Available	Available	
5013	LOV_SAP_CONNECTOR_STATE	WSG 9.4	3	Planned	Planned	
5100	LOV_NF_COPA_TT_STATE		1	ENTERED	New	
5100	LOV_NF_COPA_TT_STATE		3	CHECKED		
5100	LOV_NF_COPA_TT_STATE		4	PROCESSING		
5100	LOV_NF_COPA_TT_STATE		5	INWORK	InProgress	
5100	LOV_NF_COPA_TT_STATE		6	CLOSED	Closed	
5100	LOV_NF_COPA_TT_STATE		7	CANCELLED	Cancelled	
5100	LOV_NF_COPA_TT_STATE		8	RESOLVED	Resolved	

5100	LOV_NF_COPA_TT_STATE		10	PENDING	Pending	
5100	LOV_NF_COPA_TT_STATE		14	EXCEPTION		
5100	LOV_NF_COPA_TT_STATE		15	PRE_REJECTED	PreRejected	
5100	LOV_NF_COPA_TT_STATE		16	CANCEL PENDING	Cancel pending	
5101	LOV_NF_COPA_TT_OBJECT_TYP E		1	COPA Incoming TT		
5101	LOV_NF_COPA_TT_OBJECT_TYP E		2	COPA Outgoing TT		
5102	LOV_TT_COPA_ITSM_PROBLEM_ CODE1		400	Physical Access	1600	
5103	LOV_COPA_SA_SLA		1	KoPa-Standard	KOPA-STANDARD	
5103	LOV_COPA_SA_SLA		2	KoPa-Premium	KOPA-PREMIUM	
5104	LOV_TT_COPA_VISITCONDUCTE D		1	Yes	Yes	
5104	LOV_TT_COPA_VISITCONDUCTE D		2	No	No	
5105	LOV_TT_COPA_ITSM_PROBLEM_ CODE2		800	Unknown	4600	
5106	LOV_TT_COPA_ITSM_PROBLEM_ CODE3		900	Unknown Error	5600	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		1	infrastructure change created	1000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		2	on site action required	2000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		3	order approval	3000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		4	registration approval	4000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		5	supplier delivery	5000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		6	returned by support contact	6000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		7	third-party vendor action required	7000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		8	client action required	8000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		9	infrastructure change	9000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		10	requirement	10000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		11	future improvements	11000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		12	Original incident pending	12000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		13	deferred by customer	13000	
5107	LOV_TT_COPA_ITSM_INCIDENT_ STATE_REASON		14	incident monitoring	14000	

	STATE_REASON					
5107	LOV_TT_COPA_ITSM_INCIDENT_STATE_REASON		15	customer resubmission required	15000	
5107	LOV_TT_COPA_ITSM_INCIDENT_STATE_REASON		16	temporary corrective action	16000	
5107	LOV_TT_COPA_ITSM_INCIDENT_STATE_REASON		17	no further action required	17000	
5107	LOV_TT_COPA_ITSM_INCIDENT_STATE_REASON		19	automatic solution reported	19000	
5107	LOV_TT_COPA_ITSM_INCIDENT_STATE_REASON		20	no causal CI anymore	20000	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		1	queued	queued	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		2	openActivate	openActivate	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		3	openActivate.onsite	openActivate.onsite	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		4	deferred.scheduled	deferred.scheduled	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		5	cleared	cleared	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		6	closed	closed	
5108	LOV_TT_COPA_ITSM_INCIDENT_STATE		7	closed.cancelled	closed.cancelled	
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		103	OMDF-FAN	1003	WSG 9.6
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		115	OTO	7000	
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		116	Inhouse Cable	7042	WSG 9.7
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		118	BEP	7004	
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		119	Drop Cable	7005	
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		120	DP - Splice Closure	7006	
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		131	Feeder Cable	7007	WSG 9.6
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		132	Overhead Line	7065	WSG 9.6
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		133	No Fault Clearance	7025	WSG 9.6
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		135	Repair not Possible	7024	Kü
5109	LOV_TT_COPA_RESOLUTION_C ODE_1		136	BEB-OMDF	7002	Kü
5110	LOV_TT_COPA_RESOLUTION_C		201	Fiber- / Cable cut	2001	

	ODE_2					
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		203	Splicing wrong	2003	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		204	Connection/Installation mistake	2004	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		209	Fibre Cut	8001	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		210	Attenuation	8002	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		211	Incorrect Splice	8003	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		213	Third Party Damaging	8021	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		214	Damage	8045	
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		215	Defective mounting	8013	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		216	Everything ok	8069	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		217	Customer never reached	8063	WSG 9.7
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		218	Damage by animals	8090	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		219	Dirty Connector	8091	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		220	Material defect	8092	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		221	natural hazard	8093	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		222	Not Responsible	8094	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		223	System not ready	8095	WSG 9.6
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		224	No IP Address Allocation	8038	WSG 9.7
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		225	Configuration or Profil Error	8041	WSG 9.7
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		226	Wrong Position Connected	8004	Kü
5110	LOV_TT_COPA_RESOLUTION_C ODE_2		227	OK from Customer	8067	Kü
5111	LOV_TT_COPA_RESOLUTION_C ODE_3		1	Undefined_1	0	
5112	LOV_COPA_TT_STATE		1	ENTERED	New	
5112	LOV_COPA_TT_STATE		3	CHECKED		
5112	LOV_COPA_TT_STATE		4	PROCESSING		
5112	LOV_COPA_TT_STATE		5	INWORK	InProgress	

5112	LOV_COPA_TT_STATE		6	CLOSED	Closed	
5112	LOV_COPA_TT_STATE		7	CANCELLED	Cancelled	
5112	LOV_COPA_TT_STATE		8	RESOLVED	Resolved	
5112	LOV_COPA_TT_STATE		10	PENDING	Pending	
5112	LOV_COPA_TT_STATE		14	EXCEPTION		
5112	LOV_COPA_TT_STATE		15	PRE_REJECTED	PreRejected	
5112	LOV_COPA_TT_STATE		16	CANCEL PENDING	Cancel pending	
5113	LOV_NF_CUSTOMER_OBJECT_T YPE		1	Network Customer Notification Alarm		
5113	LOV_NF_CUSTOMER_OBJECT_T YPE		2	FiberPort Upgrade Announcement		
5113	LOV_NF_CUSTOMER_OBJECT_T YPE		3	FiberPort Upgrade Completion		
5114	LOV_NF_CUSTOMER_OBJECT_S TATE		1	COMPLETED		
6000	LOV_IPPOOL_SESSION_TYPE	sessionType	2	DHCP		
9001	LOV_TRANS_TYPE	transType	1	WORK_ORDER		
9001	LOV_TRANS_TYPE	transType	2	VOICE_MESSAGE		
9001	LOV_TRANS_TYPE	transType	3	ACCESS_TICKET		
9001	LOV_TRANS_TYPE	transType	4	WORK_TICKET		
9001	LOV_TRANS_TYPE	transType	5	ALARM		
9002	LOV_BB_PRIO_FLAG		1	001_LowPriority	001	
9002	LOV_BB_PRIO_FLAG		2	002_MediumPriority	002	
9002	LOV_BB_PRIO_FLAG		3	003_HighPriority	003	
9002	LOV_BB_PRIO_FLAG		4	004_NoDosage	004	
9002	LOV_BB_PRIO_FLAG		5	005_SPT	005	
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	1	Order Type is		Order Type is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	2	BB Type new is		BB Type new is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	3	BB Type existing is		BB Type existing is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	4	Terco Article new is		Terco Article new is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	5	Terco Article existing is		Terco Article existing is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	6	Customer Class new is		Customer Class new is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	7	Customer Class existing is		Customer Class existing is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	8	Contract Element new is		Contract Element new is
9003	LOV_ACTION_DEF	LOV_ACTION_ DEF	9	Contract Element existing is		Contract Element existing is

9003	LOV_ACTION_DEF	LOV_ACTION_DEF	10	Message Type Category is		Message Type Category is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	11	Open Pipe Speed has changed		Open Pipe Speed has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	12	DN Type is unchanged		DN Type is unchanged
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	13	DN_VN is unchanged		DN_VN is unchanged
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	14	BACK_MESSAGE_ID is		BACK_MESSAGE_ID is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	15	PROCESS_FLOW_NUMBER is		PROCESS_FLOW_NUMBER is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	16	New Open Pipe Speed > Existing Open Pipe Speed		New Open Pipe Speed > Existing Open Pipe Speed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	17	Service Speed has changed		Service Speed has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	18	Obsolete: New Service Speed > Existing Service Speed		Obsolete: New Service Speed > Existing Service Speed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	19	Existing Open Pipe Speed > New Open Pipe Speed		Existing Open Pipe Speed > New Open Pipe Speed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	20	TV Speed > New Open Pipe Speed		TV Speed > New Open Pipe Speed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	21	Kind of Creation is		Kind of Creation is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	22	BB Access is		BB Access is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	23	DN Type existing is		DN Type existing is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	24	OMS Order ID is NULL		OMS Order ID is NULL
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	25	Session_Type has changed		Session_Type has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	26	Is VoBB possible		Is VoBB possible
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	27	BB Device Location has changed		BB Device Location has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	28	Qualification with additional Service		Qualification with additional Service
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	29	BBCS at new location / with new access type possible		BBCS at new location / with new access type possible
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	31	Interleave_Mode has changed		Interleave_Mode has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	32	Session Type new is		Session Type new is

9003	LOV_ACTION_DEF	LOV_ACTION_DEF	33	Session Type existing is		Session Type existing is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	34	Pool_Type has changed		Pool_Type has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	35	BB_Type has changed		BB_Type has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	36	Combined Ordering 3Play-R5 (Internet-Service included)		Combined Ordering 3Play-R5 (Internet-Service included)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	37	Effective-Speed has changed		Effective-Speed has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	38	Port-Relocation		Port-Relocation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	39	Order related to ISP_CHANGE		Order related to ISP_CHANGE
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	40	APV OP-Code is		APV OP-Code is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	41	Activation		Activation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	42	ISP driven		ISP driven
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	43	Crossover relevant		Crossover relevant
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	44	TDM/Standalone change		TDM/Standalone change
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	45	Time $t \geq T - y$		Time $t \geq T - y$
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	46	Time $t \geq T - x$		Time $t \geq T - x$
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	47	Time $t \geq T - n2$		Time $t \geq T - n2$
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	48	Time $t \geq T - n1$		Time $t \geq T - n1$
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	49	SG-MM = 1 (terminiert)		SG-MM = 1 (terminiert)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	50	P3171 06: NEUAS = "zugeteilt"		P3171 06: NEUAS = "zugeteilt"
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	51	Time $t \geq CWD - n2$		Time $t \geq CWD - n2$
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	52	Copying for ISP is enabled		Copying for ISP is enabled
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	53	Voice activation done		Voice activation done
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	54	Voice deactivation done		Voice deactivation done
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	56	Voice activation initiated		Voice activation initiated
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	57	Einschalt-Begehren (30x0.11)		Einschalt-Begehren (30x0.11)

9003	LOV_ACTION_DEF	LOV_ACTION_DEF	58	Einschalt-Meldung (30x1.09)		Einschalt-Meldung (30x1.09)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	59	Einschalt-Bestaetigung (30x1.10)		Einschalt-Bestaetigung (30x1.10)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	60	Ausschalt-Meldung (31x1.07)		Ausschalt-Meldung (31x1.07)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	61	Ausschalt-Bestaetigung (31x1.08)		Ausschalt-Bestaetigung (31x1.08)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	62	Order not yet in process		Order not yet in process
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	63	Process driven cancellation		Process driven cancellation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	64	Office supports APV Version		Office supports APV Version
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	65	Valid SZF <= CWD Voice found		Valid SZF <= CWD Voice found
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	66	SAT-OK (PDT)		SAT-OK (PDT)
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	67	S_D_UEB is		S_D_UEB is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	68	OP Status in		OP Status in
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	69	Net driven		Net driven
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	70	Kind of Creation "Synch.w.Voice"		Kind of Creation "Synch.w.Voice"
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	71	Durchdringer		Durchdringer
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	72	ADSL emulated new		ADSL emulated new
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	73	ADSL emulated existing		ADSL emulated existing
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	74	Manually cancelled voice driven create order exists		Manually cancelled voice driven create order exists
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	75	PONR Activation reached		PONR Activation reached
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	76	PONR Deactivation reached		PONR Deactivation reached
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	77	Inconsistency Group		Inconsistency Group
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	78	Inconsistency Pattern 1		Inconsistency Pattern 1
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	79	Inconsistency Pattern 2		Inconsistency Pattern 2
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	80	Response cancelled voice driven create order exists		Response cancelled voice driven create order

						exists
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	81	Fair Use Speed On/Off		Fair Use Speed On/Off
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	82	Network New is		Network New is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	83	Network Existing is		Network Existing is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	84	Contract Element Order is		Contract Element Order is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	85	Port-Change		Port-Change
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	86	PSD Class has changed		PSD Class has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	87	GAIA-ID has changed		GAIA-ID has changed
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	88	Completed Provisioning Path is		Completed Provisioning Path is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	90	Internal Reference is		Internal Reference is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	91	Synch Type is		Synch Type is
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	92	DBC Adoption		DBC Adoption
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	100	Create Real Order		Create Real Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	140	GetXdslPort by DN/NSN		GetXdslPort by DN/NSN
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	141	GetXdslPort by Splitter-Port		GetXdslPort by Splitter-Port
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	150	Continue with 2nd Way		Continue with 2nd Way
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	200	Virtual Order state change		Virtual Order state change
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	300	Create Virtual Order		Create Virtual Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	400	MUT_CODE in case of no real or virtual orders		MUT_CODE in case of no real or virtual orders
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	500	Update FIB in case of no real or virtual orders		Update FIB in case of no real or virtual orders
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	600	Reschedule voice messages		Reschedule voice messages
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	610	Inactivate voice messages		Inactivate voice messages
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	700	Reject Data Correction		Reject Data Correction
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	710	Generate Grooming Entry		Generate Grooming Entry

9003	LOV_ACTION_DEF	LOV_ACTION_DEF	800	Synchronize with Voice Activation		Synchronize with Voice Activation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	805	Synchronize with Voice Deactivation		Synchronize with Voice Deactivation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	820	Update LL_ID		Update LL_ID
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	825	Update WOS_ID		Update WOS_ID
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	850	Embed Order		Embed Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	860	Chain Order		Chain Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	865	Hold Order 02.01.2099		Hold Order 02.01.2099
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	866	Hold Order 31.12.2099		Hold Order 31.12.2099
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	870	Submit Order		Submit Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	880	Reset Order		Reset Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	890	Cancel Order		Cancel Order
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	900	Signal PONR		Signal PONR
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	910	Reserve Port		Reserve Port
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	920	Cancel Portreservation		Cancel Portreservation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	930	Trigger process driven annulation		Trigger process driven annulation
9003	LOV_ACTION_DEF	LOV_ACTION_DEF	940	Trigger P5202		Trigger P5202
9006	LOV_TIBCO_ACCESS_PROTOCOL	AccessProtocoll	1	BX	BX	
9006	LOV_TIBCO_ACCESS_PROTOCOL	AccessProtocoll	2	ADSL	ADSL	
9006	LOV_TIBCO_ACCESS_PROTOCOL	AccessProtocoll	3	SDSL	SDSL	
9006	LOV_TIBCO_ACCESS_PROTOCOL	AccessProtocoll	4	VDSL	VDSL2	
9008	LOV_SITE_CATEGORY	Site Category	6	RUS	Regional Übertragungsstelle	
9008	LOV_SITE_CATEGORY	Site Category	7	AVE	Abgesetzte Vermittlungseinheit	
9008	LOV_SITE_CATEGORY	Site Category	8	PUS-IN	Primär Übertragungsstelle (Indoor)	
9008	LOV_SITE_CATEGORY	Site Category	9	PUS-OC	Primär Übertragungsstelle (Outdoor Cabinet)	
9008	LOV_SITE_CATEGORY	Site Category	21	PUS-IC	Primär Übertragungsstelle (Indoor Cabinet)	

9008	LOV_SITE_CATEGORY	Site Category	28	PUS-S	Fibre To The Street (sealed Outdoor, DP, FTTS)	
9008	LOV_SITE_CATEGORY	Site Category	29	PUS-B	Fibre To The Building (sealed Indoor, FTTB)	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	1	capable	capable	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	2	friendly	friendly	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	3	forced friendly	forced friendly	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	4	disturber	disturber	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	5	Capable, but firmware upgrade necessary (Not Capable)	Capable, but firmware upgrade necessary (Not Capable)	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	6	Friendly, but firmware upgrade necessary (Not Capable)	Friendly, but firmware upgrade necessary (Not Capable)	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	7	Not capable	Not capable	
9009	LOV_CPE_CAPABILITY_OVERALL	Vectoring Capability	8	Capable, but G.fast SFP needed (not capable)	Capable, but G.fast SFP needed (not capable)	
9010	LOV_LL_STATE_BB	LL State BB	0	na	na	
9010	LOV_LL_STATE_BB	LL State BB	1	complete	complete	
9010	LOV_LL_STATE_BB	LL State BB	2	incomplete	incomplete	
9010	LOV_LL_STATE_BB	LL State BB	3	incompleteRewiring	incompleteRewiring	
9011	LOV_GREETING_CODE	Greeting Code	1	Mr.	Mr.	
9011	LOV_GREETING_CODE	Greeting Code	2	Ms.	Ms.	
9011	LOV_GREETING_CODE	Greeting Code	3	Firm	Firm	
9011	LOV_GREETING_CODE	Greeting Code	4	Unknown	Unknown	
9012	LOV_REMINDER_PROCESS	Reminder Process	1	first reminder at exchange date, second reminder after 5 days	first reminder at exchange date, second reminder after 5 days	
9012	LOV_REMINDER_PROCESS	Reminder Process	2	first reminder at exchange date, no second reminder	first reminder at exchange date, no second reminder	
9013	LOV_TT_BBCS_ITSM_PROBLEM_CODE_1		1	Physical Access	1600	
9014	LOV_TT_BBCS_ITSM_PROBLEM_CODE_2		1	BBCS-F	4613	
9015	LOV_TT_BBCS_ITSM_PROBLEM_CODE_3		1	No Signal	5631	
9015	LOV_TT_BBCS_ITSM_PROBLEM_CODE_3		2	No Connection	5626	
9015	LOV_TT_BBCS_ITSM_PROBLEM_CODE_3		3	Performance	5635	
9015	LOV_TT_BBCS_ITSM_PROBLEM_CODE_3		4	Interruption	5627	
9015	LOV_TT_BBCS_ITSM_PROBLEM_CODE_3		5	LinkTest NOK	5643	added Juni15 Release
9016	LOV_TT_BBCS_ITSM_RESOLUTI		1	OTO	7000	

	ON_CODE_1					
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		2	Inhouse Cable	7042	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		3	BEP-OMDF	7002	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		4	Breakout Cable	7003	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		5	BEP	7004	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		9	OMDF	7008	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		10	No Fault Clearance, Everything OK	7023	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		15	Fulfillment Chain	7038	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		16	SFP	7030	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		17	FAN Port	7029	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		19	BNG	7031	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		20	No Fault Clearance	7025	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		21	Repair not possible	7024	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		22	Router	7016	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		23	XMDf	7012	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		24	Patch Cable	7020	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		25	OMDF-FAN	1003	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		0	Unknown	0	
9016	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_1		18	OMDF-OTO	7017	
9017	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_2		1	Fiber Cut	8001	
9017	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_2		2	Attenuation	8002	
9017	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_2		3	Incorrect Splice	8003	
9017	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_2		4	Material defect	8092	Doppelbelegung 8004, Change to 8222
9017	LOV_TT_BBCS_ITSM_RESOLUTI ON_CODE_2		6	Defective Mounting	8013	

9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		13	Defective	8044	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		14	Damage	8045	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		15	Configuration or Profil Error	8041	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		16	Customer never reached	8063	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		17	Everything ok	8069	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		18	No IP Address Allocation	8038	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		19	Wrong Position Connected	8004	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		20	Dirty Connector	8091	INC000001902874
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		21	No confirmation from Customer	8005	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		22	Wrong Patching	8222	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		23	OK from Customer	8067	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		24	Not Responsable	8094	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		25	System not ready	8095	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		26	Reset	8006	
9017	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_2		0	Undefined	0	
9018	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_3		1	Inform ISP	9000	
9018	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_3		2	Temporary Solution	9001	
9018	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_3		3	Breakout Cable Change	9002	
9018	LOV_TT_BBCS_ITSM_RESOLUT ON_CODE_3		0	Undefined	0	
9019	LOV_TT_BBCS_ITSM_INCIDENT_ STATE		1	queued	queued	
9019	LOV_TT_BBCS_ITSM_INCIDENT_ STATE		2	openActivate	openActivate	
9019	LOV_TT_BBCS_ITSM_INCIDENT_ STATE		3	openActivate.onsite	openActivate.onsite	
9019	LOV_TT_BBCS_ITSM_INCIDENT_ STATE		4	deferred.scheduled	deferred.scheduled	
9019	LOV_TT_BBCS_ITSM_INCIDENT_ STATE		5	cleared	cleared	

9019	LOV_TT_BBCS_ITSM_INCIDENT_STATE		6	closed	closed	
9019	LOV_TT_BBCS_ITSM_INCIDENT_STATE		7	closed.cancelled	closed.cancelled	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		1	Infrastruktur-Change erstellt	1000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		2	Aktion vor Ort erforderlich	2000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		3	Bestellgenehmigung	3000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		4	Registrierungsgenehmigung	4000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		5	Lieferantenlieferung	5000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		6	Vom Support-Kontakt zurückgestellt	6000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		7	Auftrag durch SCS-Partner in Bearbeitung	7000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		8	Client-Aktion erforderlich	8000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		9	Infrastruktur-Change	9000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		10	Anforderung	10000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		11	Zukünftige Verbesserungen	11000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		12	Ausstehender Original-Incident	12000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		13	Vom Kunden zurückgestellt	13000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		14	Incident beobachten	14000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		15	Kunden-Wiedervorlage erford.	15000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		16	Temporäre Korrekturmassnahmen	16000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		17	Keine weiteren Aktion erford.	17000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		19	Automat. Lösung berichtet	19000	
9020	LOV_TT_BBCS_ITSM_INCIDENT_STATE_REASON		20	Kein kausales CI mehr	20000	
9021	LOV_WSG_CONTEXT		1	BBCS-Order		
9021	LOV_WSG_CONTEXT		2	BBCS-Order Fiber		
9021	LOV_WSG_CONTEXT		3	BBCS-Access Ticket TT		
9021	LOV_WSG_CONTEXT		4	BBCS-Access Ticket TT Fiber		
9021	LOV_WSG_CONTEXT		5	FA-Order		

9021	LOV_WSG_CONTEXT		6	FA-TT		
9021	LOV_WSG_CONTEXT		7	COPA Order		
9021	LOV_WSG_CONTEXT		8	COPA Incident Ticket		
9021	LOV_WSG_CONTEXT		9	Change Ticket		
9025	LOV_TECHNOLOGY_TYPE	WSG 9.4	1	VDSL2	VDSL2	
9025	LOV_TECHNOLOGY_TYPE	WSG 9.4	2	VDSL Vectoring	VDSL Vectoring	
9025	LOV_TECHNOLOGY_TYPE	WSG 9.4	3	G.FAST	G.FAST	neuer Eintrag für Nov15
9034	LOV_REPORT_TYPE	WSG 9.5	2	OtoOmdf		
9034	LOV_REPORT_TYPE	WSG 9.5	1	OmdfXmdf		
9034	LOV_REPORT_TYPE	WSG 9.5	3	OtoSap		
9034	LOV_REPORT_TYPE	WSG 9.5	4	UMSAFiber		
9993 13	LOV_TRANS_APPL_CONTEXT	WSG 9.5	1	DEFAULT		
9993 13	LOV_TRANS_APPL_CONTEXT	WSG 9.5	2	WSG		
9993 13	LOV_TRANS_APPL_CONTEXT	WSG 9.5	3	COPA		
9993 13	LOV_TRANS_APPL_CONTEXT	WSG 9.5	4	INFOSRV		
9993 13	LOV_TRANS_APPL_CONTEXT	WSG 9.5	5	ALO		